

YASEAU 101
CRYSTAL CONVERSION INFORMATION

REPLACE THE 10 METER CRYSTALS WITH

A--32.02 covers 26.0 to 26.5

B--32.52 covers 26.5 to 27.0

C--33.02 covers 27.0 to 27.5

D--33.52 covers 27.5 to 28.0

THIS WILL ALLOW OUT OF BAND COVERAGE FOR THE ABOVE RADIO.

SWAN SYGNET
MODEL 270
11 M CONVERSION

To use this radio on 27.000MHZ to 28.000MHZ the modification is an easy one.

- (1) Remove the case and locate the VFO in the front right cover.
- (2) Remove the cover and locate C.1601 #5PF and remove this cap.
- (3) Install a 10PF in its place and reinstall the cover.
- (4) Then calibrate C160Z with a non metallic (plastic) screw driver. (28.MHZ=27.000)
- (5) The modification is now complete. Reinstall the top cover.

*****GOOD LUCK*****