

This Manual is provided by  
***CBTricks.com***

Someone who wanted to help you repair your equipment put together this information.

## Cobra 140GTL Parts List

If you would like to help us put more manuals online support us.

**If you would like to help with this project let us know.**

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

**Thank you for any support you can give.**

# BILL OF MATERIAL FOR COBRA 140GTL

CIRCUIT SYMBOL	DESCRIPTION	DYNASCAN PART NO.
<b>SEMICONDUCTORS</b>		
IC-1	Integrated Circuit,	UHIC-007 ..... 307-143-9-001
IC-2	Integrated Circuit,	MB8719 ..... 307-128-9-002
IC-3	Integrated Circuit,	AN612 ..... 307-143-9-002
IC-4	Integrated Circuit,	TA7222P ..... 307-143-9-003
IC-5	Integrated Circuit,	MB3756 ..... 307-133-9-005
IC-6	Integrated Circuit,	SO42P ..... 307-143-9-004
FET-1	Field Effect Transistor,	2SK19-BL ..... 182-037-9-001
TR-7,14,30,31	Transistor,	2SA733-P ..... 177-020-9-001
TR-36	Transistor,	2SC458-C ..... 176-048-9-002
TR-4,5,8,11,13,15,20,27, 28,29,32,33,35,37	Transistor,	2SC945A-Q ..... 176-062-9-001
TR-34	Transistor,	2SC1419-C ..... 176-055-9-004
TR-9,18,17	Transistor,	2SC1674-L ..... 176-081-9-002
TR-1,2,6,10,12,19,21,22, 23,24,25,42	Transistor,	2SC1675-L ..... 176-065-9-001
TR-3,16	Transistor,	2SC1730-L ..... 176-073-9-001
TR-40	Transistor,	2SC496-O ..... 176-087-9-001
TR-41	Transistor,	2SC1969-B ..... 176-087-9-002
TR-38	Transistor,	2SC1973 ..... 176-073-9-003
TR-39	Transistor,	2SC1306 ..... 172-024-9-002
D-3,4,5,6,7,8,10,11,12, 15,16,17,18,19,20,23, 24,25,26,27,28,29,30, 31,32,33,34,35,36,38, 39,40,41,43,44,48,49, 50	Diode,	1S1588 ..... 151-051-9-001
D-1,2,9,21,22,42	Diode,	1N60 ..... 150-001-9-005
D-13,14	Diode,	MC301 ..... 151-073-9-001
D-45	Diode,	SR1K-2 ..... 151-045-9-001
D-402	Diode, LED,	TLRG101 ..... 158-020-9-001
D-401	Diode, LED,	TLR-321 ..... 158-014-9-001
D-46	Diode, Varistor,	MV-1Y ..... 004-175-9-001
D-47	Diode, Varistor,	MV-13YH ..... 153-011-9-001
D-37	Diode, Varicap,	1S2687D ..... 153-008-9-001
<b>INDUCTORS</b>		
L-1	Coil,	LA-038 ..... 060-018-9-001
L-27	Coil,	LA-160 ..... 060-025-9-008
L-2	Coil,	LA-179 ..... 060-025-9-010
L-14	Coil,	LA-195 ..... 060-030-9-001
L-13	Coil,	LA-216 ..... 060-030-9-002
L-19	Coil,	LA-217 ..... 060-030-9-003
L-20	Coil,	LA-218 ..... 060-030-9-004
L-26	Coil,	LA-219 ..... 060-030-9-005
L-28	Coil,	LA-220 ..... 060-030-9-006
L-17	Coil,	LA-223 ..... 060-030-9-007
L-29	Coil,	LA-254 ..... 060-030-9-008
L-3	Coil,	LA-255 ..... 060-030-9-009

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**INDUCTORS (Continued)**

L-18	Coil,	LA-256 .....	060-030-9-010
L-6	Coil,	LA-257 .....	060-030-9-011
L-7	Coil,	LA-258 .....	060-030-9-012
L-8	Coil,	LA-259 .....	060-030-9-013
L-9	Coil,	LA-260 .....	060-030-9-014
L-10	Coil,	LA-261 .....	060-030-9-015
L-5	Coil,	LA-262 .....	060-030-9-016
L-4	Coil,	LA-263 .....	060-030-9-017
L-53,404,405,50,51,52	Coil,	LD-077 .....	763-084-9-001
L-36,39	Coil,	LD-019 .....	044-053-9-001
L-401,402	Coil,	LD-013 .....	044-043-9-022
L-403	Coil,	LD-089 .....	044-048-9-002
L-31,34	Coil,	LD-087 .....	044-048-9-003
L-30	Coil,	LD-096 .....	044-053-9-002
L-35,33	Coil,	LD-098 .....	044-053-9-003
L-32	Coil,	LD-101 .....	044-053-9-004
L-37,38	Coil,	LE-051 .....	044-043-9-008
L-12,25	Micro Inductor,	LZ-012 100 $\mu$ H .....	041-088-9-003
L-11,15,16,21,22,23,24	Micro Inductor,	LZ-012 470 $\mu$ H .....	041-088-9-004
T-1	Choke Coil, Line Filter,	TF-147 .....	046-023-9-001

**SEMI-FIXED & VARIABLE RESISTORS**

VR-8	Resistor, Semi-Fixed,	RV-189 500 ohm B .....	008-342-9-001
VR-6,9	Resistor, Semi-Fixed,	RV-189 5K ohm B .....	008-316-9-004
VR-1,5,7	Resistor, Semi-Fixed,	RV-189 10K ohm B .....	008-342-9-002
VR-10	Resistor, Semi-Fixed,	RV-189 100K ohm B .....	008-316-9-001
VR-2	Resistor, Semi-Fixed,	RV-189 1K ohm B .....	008-334-9-001
VR-3	Resistor, Semi-Fixed,	RV-189 3K ohm B .....	008-323-9-001
VR-401	Resistor, Variable,	RV-204 100K ohm B, Squelch .....	008-342-9-003
VR-402	Resistor, Variable,	RV-203 20K ohm B, VoiceLock .....	008-342-9-004
VR-403	Resistor, Variable,	RV-205 10K ohm A, Volume Control .....	008-342-9-005
VR-404	Resistor, Variable,	RV-316 10K ohm B, RF Gain .....	008-342-9-006

**FIXED RESISTORS**

R-185	Resistor, Metallic Film,	220 ohm 1W $\pm$ 10% .....	001-001-6-221
R-112	Resistor, Metallic Film,	100 ohm 1W $\pm$ 10% .....	002-001-6-101
R-150	Resistor, Carbon Film,	270 ohm 1/2W $\pm$ 5% .....	002-102-5-271
R-403	Resistor, Carbon Film,	1K ohm 1/2W $\pm$ 5% .....	002-102-5-102
R-148	Resistor, Carbon Composit	10K ohm 1/2W $\pm$ 10% .....	001-102-6-103
R-55	Resistor, Carbon Film,	2.2 ohm 1/8W $\pm$ 5% .....	002-108-5-229
R-153	Resistor, Carbon Film,	4.7 ohm 1/8W $\pm$ 5% .....	002-108-5-479
R-163	Resistor, Carbon Film,	10 ohm 1/8W $\pm$ 5% .....	002-108-5-100
R-162	Resistor, Metallic Film,	100 ohm 1/2W $\pm$ 10% .....	001-102-6-101
R-8,21,62,19	Resistor, Carbon Film,	68 ohm 1/8W $\pm$ 5% .....	002-108-5-680
R-23,42,43,46,83,127, 149,156,157,158,159	Resistor, Carbon Film,	100 ohm 1/8W $\pm$ 5% .....	002-108-5-101
R-7,61	Resistor, Carbon Film,	150 ohm 1/8W $\pm$ 5% .....	002-108-5-151
R-4,53,56,106,129,152	Resistor, Carbon Film,	220 ohm 1/8W $\pm$ 5% .....	002-108-5-221
R-14,151,155,179,182	Resistor, Carbon Film,	330 ohm 1/8W $\pm$ 5% .....	002-108-5-331
R-3	Resistor, Carbon Film,	470 ohm 1/8W $\pm$ 5% .....	002-108-5-471
R-85,176,194	Resistor, Carbon Film,	560 ohm 1/8W $\pm$ 5% .....	002-108-5-561
R-26,118	Resistor, Carbon Film,	680 ohm 1/8W $\pm$ 5% .....	002-108-5-681

CIRCUIT SYMBOL	DESCRIPTION	DYNASCAN PART NO.
<b>RESISTORS (Continued)</b>		
R-172,191	Resistor, Carbon Film, 150 ohm 1/8W ±5%	002-108-5-151
R-54	Resistor, Carbon Film, 270 ohm 1/8W ±5%	002-108-5-271
R-178	Resistor, Carbon Film, 1.2K ohm 1/8W ±5%	002-108-5-122
R-135,401,402,404,405, 406,407,408,409,410, 411,412,413	Resistor, Carbon Film, 1.8K ohm 1/8W ±5%	002-108-5-182
R-48,71,105,60,125	Resistor, Carbon Film, 1.5K ohm 1/8W ±5%	002-108-5-152
R-34,36,79,77,78,110, 131,154	Resistor, Carbon Film, 2.2K ohm 1/8W ±5%	002-108-5-222
R-6,72,192,183	Resistor, Carbon Film, 2.7K ohm 1/8W ±5%	002-108-5-272
R-2,16,18,68,25,31,50,189, 58,89,97,98,117,124,120	Resistor, Carbon Film, 3.3K ohm 1/8W ±5%	002-108-5-332
R-30,35,39,80,88,91,93, 107,121,126,128,132, 144,145,186,32,114,193	Resistor, Carbon Film, 1K ohm 1/8W ±5%	002-108-5-102
R-38,177	Resistor, Carbon Film, 3.9K ohm 1/8W ±5%	002-108-5-392
R-20,37,111,123	Resistor, Carbon Film, 4.7K ohm 1/8W ±5%	002-108-5-472
R-136	Resistor, Carbon Film, 5.6K ohm 1/8W ±5%	002-108-5-562
R-76	Resistor, Carbon Film, 6.8K ohm 1/8W ±5%	002-108-5-682
R-141	Resistor, Carbon Film, 8.2K ohm 1/8W ±5%	002-108-5-822
R-11,12,13,15,29,40,44, 90,94,99,109,181,130, 133,134,137,143,140, 104	Resistor, Carbon Film, 10K ohm 1/8W ±5%	002-108-5-103
R-24,74	Resistor, Carbon Film, 12K ohm 1/8W ±5%	002-108-5-123
R-102	Resistor, Carbon Film, 15K ohm 1/8W ±5%	002-108-5-153
R-142,1	Resistor, Carbon Film, 18K ohm 1/8W ±5%	002-108-5-183
R-41,116,147,108,187	Resistor, Carbon Film, 22K ohm 1/8W ±5%	002-105-5-223
R-73,75,100	Resistor, Carbon Film, 33K ohm 1/8W ±5%	002-108-5-333
R-5,28,59,64,96,66,87, 95	Resistor, Carbon Film, 47K ohm 1/8W ±5%	002-108-5-473
R-9,63,65,92	Resistor, Carbon Film, 100K ohm 1/8W ±5%	002-108-5-104
R-82	Resistor, Carbon Film, 150K ohm 1/8W ±5%	002-108-5-154
R-45	Resistor, Carbon Film, 180K ohm 1/8W ±5%	002-108-5-184
R-84	Resistor, Carbon Film, 270K ohm 1/8W ±5%	002-108-5-274
R-22	Resistor, Carbon Film, 330K ohm 1/8W ±5%	002-108-5-334
R-10	Resistor, Carbon Film, 470K ohm 1/8W ±5%	002-108-5-474
R-103,101	Resistor, Carbon Film, 1M ohm 1/8W ±5%	002-108-5-105
R-81	Resistor, Carbon Film, 100 ohm 1/8W ±5%	002-108-5-101
R-184	Resistor, Carbon Film, 150 ohm 1/8W ±5%	002-108-5-151
R-425	Resistor, Carbon Film, 47K ohm 1/8W ±5%	002-108-5-473
R-17,19,33, 13,122	Resistor, Carbon Film, 1K ohm 1/8W ±5%	002-108-5-102
R-70	Resistor, Carbon Film, 1.8K ohm 1/8W ±5%	002-108-5-182
R-47,49,146	Resistor, Carbon Film, 1.5K ohm 1/8W ±5%	002-108-5-152
R-188	Resistor, Carbon Film, 3.3K ohm 1/8W ±5%	002-108-5-332
R-115	Resistor, Carbon Film, 6.8K ohm 1/8W ±5%	002-108-5-682
R-52,57,86,180	Resistor, Carbon Film, 10K ohm 1/8W ±5%	002-108-5-103
R-27	Resistor, Carbon Film, 33K ohm 1/8W ±5%	002-108-5-333
R-67	Resistor, Carbon Film, 390K ohm 1/8W ±5%	002-108-5-394

### CAPACITORS

C-109,13	Capacitor, Tantalum, 0.1μF 25V ±20%	027-035-9-001
C-7,19	Capacitor, Tantalum, 0.22μF 16V ±20%	027-035-9-002
C-62,63	Capacitor, Tantalum, 2.2μF 25V ±20%	027-031-9-001

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**CAPACITORS (Continued)**

C-72	Capacitor, Tantalum,	4.7 $\mu$ F	10V	$\pm 20\%$	.....	027-026-9-005
C-59,193	Capacitor, Tantalum,	1 $\mu$ F	25V	$\pm 20\%$	.....	027-035-9-003
C-84,113	Capacitor, Tantalum,	22 $\mu$ F	6.3V	$\pm 20\%$	.....	027-035-9-004
C-16,17,27,121,142	Capacitor, Electrolytic,	0.47 $\mu$ F	50V		.....	023-157-9-001
C-119,146,162,169	Capacitor, Electrolytic,	1 $\mu$ F	50V		.....	022-157-9-002
C-15,83	Capacitor, Electrolytic,	2.2 $\mu$ F	25V		.....	022-158-9-002
C-73,112	Capacitor, Electrolytic,	4.7 $\mu$ F	25V		.....	022-157-9-003
C-90,120,133	Capacitor, Electrolytic,	10 $\mu$ F	16V		.....	022-157-9-004
C-117,164	Capacitor, Electrolytic,	10 $\mu$ F	25V		.....	022-171-9-001
C-180	Capacitor, Electrolytic,	22 $\mu$ F	10V		.....	022-163-9-001
C-24,26,9,114	Capacitor, Electrolytic,	47 $\mu$ F	10V		.....	022-160-9-002
C-107	Capacitor, Electrolytic,	220 $\mu$ F	10V		.....	022-171-9-002
C-118	Capacitor, Electrolytic,	470 $\mu$ F	10V		.....	022-160-9-001
C-66	Capacitor, Electrolytic,	1000 $\mu$ F	10V		.....	022-171-9-003
C-134	Capacitor, Electrolytic,	1000 $\mu$ F	25V		.....	022-171-9-004
C-58,115	Capacitor, Polyester Film,	0.001 $\mu$ F	50V	$\pm 10\%$	.....	025-122-9-002
C-82,85	Capacitor, Polyester Film,	0.0047 $\mu$ F	50V	$\pm 10\%$	.....	025-126-9-001
C-89,93,161	Capacitor, Polyester Film,	0.01 $\mu$ F	50V	$\pm 10\%$	.....	025-121-9-002
C-86,25,194	Capacitor, Polyester Film,	0.033 $\mu$ F	50V	$\pm 10\%$	.....	025-121-9-004
C-71,88,108,168,190	Capacitor, Polyester Film,	0.047 $\mu$ F	50V	$\pm 10\%$	.....	025-121-9-006
C-28,61,79,150,153,116, 110	Capacitor, Polyester Film,	0.1 $\mu$ F	50V	$\pm 10\%$	.....	025-121-9-001
C-91	Capacitor, Polyester Film,	0.0022 $\mu$ F	50V	$\pm 10\%$	.....	030-041-9-003
C-55,111	Capacitor, Polyester Film,	0.022 $\mu$ F	50V	$\pm 10\%$	.....	025-121-9-003
C-160	Capacitor, Ceramic Disk,	1.5pF	50V	$\pm 0.25$ pF	CH	020-204-9-001
C-139,147	Capacitor, Ceramic Disk,	1pF	50V	$\pm 0.25$ pF	CH	020-180-9-001
C-38,42,44	Capacitor, Ceramic Disk,	2pF	50V	$\pm 0.25$ pF	CH	020-180-9-002
C-22,23	Capacitor, Ceramic Disk,	3pF	50V	$\pm 0.25$ pF	CH	020-204-9-002
C-36,80	Capacitor, Ceramic Disk,	4pF	50V	$\pm 0.25$ pF	CH	020-190-9-031
C-21	Capacitor, Ceramic Disk,	5pF	50V	$\pm 0.5$ pF	CH	020-204-9-003
C-65,105,126,140,132	Capacitor, Ceramic Disk,	10pF	50V	$\pm 5\%$	CH	020-181-9-009
C-171	Capacitor, Ceramic Disk,	56pF	50V	$\pm 5\%$	CH	020-192-9-001
C-29	Capacitor, Ceramic Disk,	12pF	50V	$\pm 5\%$	CH	020-190-9-033
C-76	Capacitor, Ceramic Disk,	15pF	50V	$\pm 5\%$	CH	020-186-9-001
C-64,104,166	Capacitor, Ceramic Disk,	18pF	50V	$\pm 5\%$	CH	020-204-9-004
C-57	Capacitor, Ceramic Disk,	27pF	50V	$\pm 5\%$	CH	020-204-9-005
C-43,175	Capacitor, Ceramic Disk,	33pF	50V	$\pm 5\%$	CH	020-204-9-006
C-69,70,158	Capacitor, Ceramic Disk,	47pF	50V	$\pm 5\%$	CH	020-187-9-009
C-143	Capacitor, Ceramic Disk,	68pF	50V	$\pm 5\%$	CH	020-204-9-007
C-8	Capacitor, Ceramic Disk,	82pF	50V	$\pm 5\%$	CH	020-204-9-008
C-102	Capacitor, Ceramic Disk,	100pF	50V	$\pm 5\%$	CH	020-190-9-034
C-144	Capacitor, Ceramic Disk,	39pF	50V	$\pm 5\%$	CH	020-204-9-009
C-10	Capacitor, Ceramic Disk,	100pF	50V	$\pm 10\%$	RH	020-204-9-010
C-145	Capacitor, Ceramic Disk,	180pF	50V	$\pm 10\%$	RH	020-204-9-011
C-81	Capacitor, Ceramic Disk,	270pF	50V	$\pm 10\%$	UJ	020-204-9-012
C-149,159,174	Capacitor, Ceramic Disk,	330pF	50V	$\pm 10\%$	UJ	020-204-9-013
C-148	Capacitor, Ceramic Disk,	390pF	50V	$\pm 10\%$	UJ	020-204-9-014
C-170	Capacitor, Ceramic Disk,	100pF	50V	$\pm 10\%$	SL	020-180-9-016
C-151	Capacitor, Ceramic Disk,	470pF	50V	$\pm 10\%$	UJ	020-204-9-015
C-127	Capacitor, Ceramic Disk,	220pF	50V	$\pm 10\%$	SL	020-180-9-019
C-128	Capacitor, Ceramic Disk,	470pF	50V	$\pm 10\%$	SL	020-204-9-016
C-163	Capacitor, Ceramic Disk,	120pF	50V	$\pm 10\%$	RH	020-181-9-006
C-3,6,9,30,32,34,39,40,41, 98,101,404,405,406, 407,31,165,403,415, 172,176,178,192	Capacitor, Ceramic Disk,	0.001 $\mu$ F	50V	$\pm 20\%$	YD	020-204-9-017

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**CAPACITORS (Continued)**

C-35,37,33,138,141,202, 203,204,205,135,137, 136,155,156,157,152, 154,173	Capacitor, Ceramic Disk, 0.0047 $\mu$ F 50V $\pm$ 20%	YD	020-204-9-018
C-74,48,75,67,78,94,95, 100,103,106,122,123, 124,125,129,130,131, 60,99,77,401,189,181	Capacitor, Ceramic Disk, 0.01 $\mu$ F 50V $\pm$ 20%	YD	020-204-9-019
C-1,2,4,5,12,11,18,14, 20,45,46,47,49,50, 51,52,54,56,68,87, 167,206,177,208,402	Capacitor, Ceramic Disk, 0.022 $\mu$ F 50V $\begin{matrix} -20\% \\ +80\% \end{matrix}$	YF	020-204-9-020
C-182	Capacitor, Ceramic Disk, 0.047 $\mu$ F 50V $\begin{matrix} -20\% \\ +80\% \end{matrix}$	ZF	020-204-9-021
C-207	Capacitor, Ceramic Disk, 0.1 $\mu$ F 50V $\begin{matrix} -20\% \\ +80\% \end{matrix}$	ZF	020-204-9-022
CT-1,2,3	Trimmer Capacitor, CV-028 20P		028-051-9-001
CC-1	Capacitor Array, 1000pF 50WV $\times$ 5 HA-003..		527-077-9-002

**CRYSTALS**

X-1	Quartz Crystal, QX-077, 10.24 MHz	133-014-9-001
X-4	Quartz Crystal, QX-094, 11.1125 MHz	133-019-9-001
X-3	Quartz Crystal, QX-083, 7.7975 MHz	133-019-9-002
X-2	Quartz Crystal, QX-084, 7.8025 MHz	133-019-9-003

**MISCELLANEOUS**

	Printed Circuit Board, Main	
	Printed Circuit Board, Channel Switch	
	Printed Circuit Board, LED	
	Printed Circuit Board, Mic Connector	
FT-1	Crystal Filter, FL-065	143-008-9-001
S-403	Switch, Rotary SR-191, MODE	083-235-9-001
S-401	Switch, Rotary SR-208, CHANNEL	083-235-9-002
S-405	Switch, SLIDE SW-145, NB/ANL	084-063-9-001
S-404	Switch, SLIDE SW-146, PA-CB	084-063-9-002
SP-401	Speaker, SP-050	580-027-9-001
M-401	Meter, MT-087	320-092-9-001
MIC	Microphone, MK-091 Dynamic	562-024-9-001
J-405	Antenna Connector, JK-068	772-036-9-001
J-404	Microphone Connector, JK-104	771-029-9-001
J-403	DC Power Connector, JK-052	762-020-9-001
J-401,402	Jack, JK-089, PA SP/EXT SP	773-086-9-001
	Speaker Cord, JK-082	772-038-9-003
	Crystal Socket, SK-023	749-097-9-001
TP-1,3,6,9,10	Test Point Terminal, TP-019	757-028-9-002
TP-2,4,11	Test Point Terminal, TP-020	
TP-7,8	Test Point Terminal, TP-027	757-032-9-002
F-401	Fuse, FS-001 4A	191-251-3-004
	Insulator for IC-5	350-006-9-001
	Insulator for TR34,39,41	342-039-9-001
	Tight Bushing for TR34,39,41	759-084-9-001
	Insulator for IC-4	350-007-9-001
	Flat Cable, WF-005, 3.5-35-3.5	426-035-9-001
	Flat Cable, WF-005, 3.5-50-3.5	426-035-9-002

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**MISCELLANEOUS (Continued)**

Flat Cable, WF-011, 3.5-50-3.5 .....	426-035-9-003
DC power Cord, W-070234 .....	426-035-9-004
Main Chassis, AIP 2.0t .....	
Case, Top 1.0t Black.....	272-127-9-001
Case, Bottom 1.0t Black .....	272-127-9-002
Mounting Bracket, SPCC 2.0t ZMC3 .....	251-351-9-001
Front Chassis, SPCC 1.0t ZMC3 .....	254-031-9-001
Microphone Hanger, SPCC 1.0t i3 .....	741-074-9-001
Metal Plate for earth, 0.8t .....	763-107-9-001
Front Panel .....	255-167-9-001
Channel selector knob .....	751-151-9-001
Knob for VR/SQ/RF GAIN/MODE /VOICE LOCK .....	751-095-9-002
Light shield, Channel Display .....	380-304-9-001
Channel Display Holder .....	753-009-9-002
LED Holder Rubber .....	381-085-9-001
Meter Holder .....	763-107-9-002
Screw for Mounting Bracket, Metal.....	634-088-9-001
Front Plate .....	260-152-9-001
F.C.C. Plate .....	
Rubber Washer for Mounting Bracket .....	381-085-9-002
Warning Label .....	
Screw, Pan Head 3DIA x 6, Metric .....	634-051-9-001
Screw, Flat Head, 3DIA x 6, Metric .....	634-088-9-002
Screw, Binding Head 2DIA x 5, Metric .....	634-099-9-001
Screw, Binding Head, 2.6 x 5, Metric .....	634-067-9-003
Screw, Binding Head, 2.6 x 6, Metric .....	634-099-9-002
Screw, Binding Head, 2.6 x 10, Metric .....	634-090-9-003
Screw, Binding Head, 3 x 5 Metric .....	634-067-9-002
Screw, Binding Head, 3 x 6, Metric .....	634-053-9-001
Screw, Binding Head, 3 x 8, Metric .....	634-067-9-001
Tapping Screw, Round Head 3.5DIA x 8 .....	710-021-9-001
Tapping Screw, Round Head 5DIA x 10 .....	710-029-9-002
Screw, Binding Head, Tap Tight 3 DIA x 8, Metric .....	710-036-9-002
Hex Nut, 2.6 I.D. Metric.....	653-042-9-003
Hex Nut, 3 I.D. Metric .....	653-024-9-001
Frang Nut, 3 I.D. Metric .....	653-026-9-002
Spring Washer, 2.6 I.D. ....	731-049-9-002
Lock Washer, 3.5 I.D. ....	731-041-9-001
Lock Washer, 5 I.D. ....	731-041-9-002
Lug Terminal, 3 DIA .....	345-052-9-001
Spring for Knob .....	763-084-9-004
Rivet, 3.2 DIA x 5 .....	
Styrofoam, Front .....	503-151-9-001
Styrofoam, Rear .....	503-152-9-001
Display Box .....	500-362-9-001
Master Carton .....	
Instruction Manual .....	480-232-9-001
Circuit Diagram/Bill of Material .....	499-138-9-001
F.C.C. Application Form 505.....	
Warranty Card .....	
Service Station List .....	
F.C.C. Form 555B .....	
F.C.C. Rules Part 95 .....	