

CAT. NO.	REF. NO.	DESCRIPTION	CAT. NO.	REF. NO.	DESCRIPTION
ELECTRICAL					
<u>CAPACITORS</u>			<u>CAPACITORS ,Cont'd.</u>		
C1,23,58,67,110		39Pf, 50V, ±10%	(C)	C130,144	47Mf, 16V (E)
C2,60,64,105,106		22Pf, 50V, ±10%	(C)	C134	220Mf, 16V (E)
C3		18Pf, 50V, ±10%	(C)	C135	0.082Mf, 50V, ±10% (M)
C4,51,56,85,106,179		33Pf, 50V, ±10%	(C)	C137	10Mf, 10V (E)
C5,40,70,115		82Pf, 50V, ±10%	(C)	C138	100Mf, 25V (E)
C6,63		330Pf, 50V, ±10%	(C)	C139	3.3Mf, 25V (E)
C7,33,173		120Pf, 50V, ±10%	(C)	C141	2200Mf, 16V (E)
C8,124		47mf, 10V	(E)	C168	0.01Mf, 50V, ±10% (C)
C9		0.047Mf, 50V, ±10%	(M)	C186	270Mf, 50V, ±10% (C)
C10,13,20,22,28,29,31,45,46,48,52,53,54,57,71,73,74,75,76,77,78,82,83,93,94,99,109,113,114,121,125,133,140,143,145,146,147,148,149,151,153,154,156,158,159,161,162,163,164,169,170,175,178,181,182,183,184,301,302		0.01Mf, 50V	(C)	(C) CERAMIC (E) ELECTROLITIC (M) MYLAR	
C11,44,47,81,157,172		1Mf, 50V	(E)	<u>TRANSISTORS & INTEGRATED CIRCUITS</u>	
C12,61,79,91,108,123,167,303		1000Pf, 50V	(C)	EA33X8704	IC1 PLL, LC7131C
C14,15,59,65,80,84,86		10Pf, 50V, ±.5%	(C)	EA33X8508	IC2 Balanced Modulation,AN612
C16,41		470Pf, 50V, ±10%	(C)	EA33X8702	IC3 Audio Pre Amp/Squelch switch AN6552
C17		180Pf, 50V, ±10%	(C)	EA33X8703	IC4 IF Amp, SN76600P
C18,25,36,49,120,142,185		0.047Mf, 50V, ±20%	(C)	EA33X8701	IC5 Audio Power Amp, AN7140
C19		4Pf, 50V, ±.25%	(C)	EA15X494	Q1 Buffer, 2SC2724C,D
C21,50,88,89		56Pf, 50V, ±10%	(C)	EA15X509	Q2 VCO, 2SC2724D
C24,42,62,111		220Pf, 50V, ±10%	(C)	EA15X509	Q3 Mixer, 2SC2724D
C26,35,152,174		150Pf, 50V, ±10%	(C)	EA15X509	Q4 Mixer, 2SC2724D
C27,30,100,104,117,119,180		4700Pf, 50V, ±10%	(C)	EA15X509	Q5 Rf, Amp, 2SC2724D
C32,39		560Pf, 50V, ±10%	(C)	EA15X428	Q6 Rf Pre-Amp, 2SC1973
C34,90		12Pf, 50V, ±10%	(C)	EA15X414	Q7 Rf Driver, 2SC2166
C37,126		0.22Mf, 50V	(E)	EA15X392	Q8 Rf Power, 2SC1969
C38		7Pf, 50V, ±.5%	(C)	EA15X509	Q9 10.240MHz Osc,2SC2724D
C43,55		2Pf, 50V, ±.25%	(C)	EA15X508	Q10 Switching, 2SC945
C65,80		100Pf, 50V, ±10%	(C)	EA15X509	Q11 10.692 MHz Osc,2SC2724D
C68,116,128,132,136,155,165,166,171,176		10Mf, 16V	(E)	EA15X404	Q12 Switching, 2SC945P
C87,96		15Pf, 50V, ±10%	(C)	EA15X509	Q13 Rf Amp, 2SC2724D
C92,97,98,131		0.04Mf, 50V, ±10%	(C)	EA15X494	Q14 Rf Amp, 2SC2724C, D
C103		4.7Mf, 25V	(E)	EA15X509	Q15 Mixer, 2SC2724D
C107		33Mf, 6.3V	(E)	EA15X251	Q16 IF Amp, 2SC1359B,C
C112		3300Pf, 50V, ±10%	(C)	EA15X386	Q17 SSB DEF, 2SC1327T,U
C118,129,150,160		22Mf, 16V	(E)	EA15X456	Q18 DC Switching, 2SD471
C122		0.022Mf, 50V, ±10%	(C)	EA15X420	Q19 Switching, 2SB564
C127		6800Pf, 50V, ±10%	(C)	EA15X456	Q20 Switching, 2SD471
				EA15X420	Q21 Switching, 2SB564
				EA15X510	Q22 AVR, 2SD235
				EA15X251	Q23 Noise Blanker,2SC1359B,C
				EA15X385	Q24 Noise Det. Blanker,2SA733-Q
				EA15X251	Q25 Noise Blanker Switch 2SC1359B,C
				EA15X325	Q26 AGC, 2SC828T
				EA15X385	Q27 ALC, 2SA733-Q
				EA15X404	Q28 SSB ALC, 2SC945T
				EA15X507	Q29 Modulation Amp, 2SD837
				EA15X508	Q30 Switching, 2SC945
				EA15X404	Q31 Switching, 2SC945P
				EA15X509	Q32 Buffer, 2SC2724D
				EA15X509	Q33 Buffer, 2SC2724C
				EA15X404	Q34 Switching, 2SC945P
				EA15X494	Q35 Rf Switching,2SC2724C,D
				EA15X404	Q36 Switching, 2SC945P
				EA15X231	Q37 Squelch switching, 2SK34 C,D
				EA15X404	Q38 Switching, 2SC945P

REPLACEMENT PARTS LIST MODEL 3-5826A

CAT. NO.	REF. NO.	DESCRIPTION	CAT. NO.	REF. NO.	DESCRIPTION
ELECTRICAL- Cont'd.					
<u>JACKS</u>			<u>FILTERS & CRYSTALS</u>		
EA41X203	J1	Antenna Jack	EA36X645	XF1	10.6935MHz
EA41X235	J2	PA/CB Jack	EA36X644	XF2	
EA41X235	J3	Ext. Speaker	EA36X643	XF3	
EA41X236	J4	DC Power Jack	EA75X6	X1	10.240MHz
EA41X176	J5	Microphone Jack	EA75X11	X2	10.692MHz

Note: 1. Parts Listed with out catalog numbers or not listed at all are non-stocked items.

Replacement Parts may be ordered from: General Electric Co., National Parts Distribution, P. O. Box 7025, Charlotte, N.C. 28217.

