Texas Star DX1600V

Texas Star 1600V

This amplifier introduced in February 2006. It has 2 x 2SC2879 transistors driving 8 x 2SC2879 transistors

Front Panel Controls

POWER (On and Off) DRIVER (Driver Only) FINALS (Finals Only) **NOTE:** When both switches are in, you are running the Driver and Finals REC AMP (Preamp to amplify receive) Variable Power Control (Only in Driver or Driver + Finals)



Rear Panel Controls

DLY Switch (SSB Delay Switch) **FAN** Switch (ON constant or automatic thermal control)

Jacks (Rear Panel) Key (for use as a CW Transmitter) RADIO (RF Input) ANT (RF Output) FAN (Fan Kit power or Remote Control) NOTE: The Mode of the FAN Jack is controlled by a switch on the Driver PCB inside the Amp. (You can set it for Remote or Fan but Not Both)

Power Chart	Input	Min. Output	Max. Output
Driver Only	4 Watts	4 watts @ 4 Amps	50 watts @ 15 Amps
Two 2SC2879	8 Watts	8.5 watts @ 6 Amps	115 watts @ 22 Amps
Transistors	16 Watts	17 watts @ 9 Amps	200 watts @ 30 Amps
	32 Watts	35 watts @ 13 Amps	300 watts @ 36 Amps

	Input	Min. Output	Max. Output
Finals Only	4 Watts	N/A	200 watts @ 55 Amps
Eight	8 Watts	N/A	400 watts @ 77 Amps
2SC2879	16 Watts	N/A	750 watts @ 103 Amps
Transistors	32 Watts	N/A	1050 watts @ 124 Amps
	64 Watts	N/A	1350 watts @ 144 Amps
	100 Watts	N/A	1500 watts @ 155 Amps
	128 Watts	N/A	1550 watts @ 161 Amps
	150 Watts	N/A	1600 watts @ 168 Amps

	Input	Min. Output	Max. Output
Driver +	2 Watts	50 watts @ 30 Amps	1000 watts @ 130 Amps
Finals	4 Watts	160 watts @ 54 Amps	1300 watts @ 158 Amps
All Ten	8 Watts	375 watts @ 80 Amps	1500 watts @ 180 Amps
Transistors	10 Watts	450 watts @ 90 Amps	1525 watts @ 185 Amps
	12 Watts	575 watts @ 100 Amps	1550 watts @ 190 Amps
	16 Watts	750 watts @ 113 Amps	1600 watts @ 200 Amps

Automatic thermal shutdown switches to protect amplifier from overheating (driver or final). There is fan kit that can replace the bottom cover, which covers the heatsink.

Remote:

Uses the same remote used for the DX1200 / DX1600. For more information go to http://www.cbtricks.com