



4 POWER LEVEL TEN METER CW TRANSMITTER

SOLID STATE • PUSHBUTTON CONTROL • RF METER

Select the power that will meet your needs to communicate. Outcom delivers four (4) power levels at a push of a button. A 1½" meter replaces conventional L.E.D. indicators so that you can monitor output levels and antenna system changes. Dependable and practical is what we're all about.

FEATURES:

- *Selectable power—four (4) power levels.
- *Pushbutton switches—lighted, engraved, and color coded.
- *Meter—indicates relative output and lights in transmit.
- *6PDT rugged relay—no "break up" by using multi-contacts.
- *Receive amplifier—10dB gain at 28MHz.
- *Power diode—prevents destruction of output transistors when unit is incorrectly connected to D.C.
- *Floating ground—operates in positive or negative grounded vehicles.
- *Stripline RF—protection against infinite VSWR; antenna problems will not destroy output transistors.

SPECIFICATIONS OF THE FORCE:

POWER OUTPUT:

Highest level - neither blue nor yellow depressed.
 Third level - press blue only.
 Second level - press yellow only.
 Lowest level - press both blue and yellow.

*R₂D₂ is an optional driver stage.

Frequency range: 28.0 thru 29.7MHz
 Input impedance: 50 ohms
 Output impedance: 50 ohms
 Receive amplifier: 10dB minimum gain at 28 MHz

| VFO | VFO with R ₂ D ₂ * installed |
|-----------|--|
| 0.5 ± 3dB | 150 ± 1dB |
| 0.375 | 110 |
| 0.25 | 75 |
| 0.125 | 40 |

Power requirements: 13.6VDC
 Overall dimensions: 3¼ x 5½ x 7¾
 Weight: 4 lbs.
 Operating temperature: -40°C thru 85°C

WARRANTY: Limited one year warranty covering parts and labor (power transistors 90 days) exclusive of shipping charges to factory. Warranty is not valid if unit has been tampered with, misused or damaged.

Outcom Communicative Electronics
 1520-J Industrial Avenue
 Escondido, CA 92025
 Phone: (714) 743-3929

Contact your dealer at:

IF IT'S NOT AN OUTCOM, YOU'RE NOT USING THE FORCE.