

AUTOMATIC MODEL CBH2265

Adjust L202 and L205 for maximum AM power.  
Adjust R207 for 100% modulation or clip D201.  
R227: RF meter adjustment  
R153: S meter adjustment  
Connect pins P6 and P7 off PLL for new frequencies.

BOMAN CBR9600

Adjust L111 and L113 for maximum RF power.  
Adjust RV105 for 100% modulation.  
RV104: RF panel meter adjustment  
RV102: S meter adjustment  
Connect pins 18 and 19 of IC101(UPD858c)  
together and jump both to pin 21 for new  
frequencies.

ALARON B-5200

Adjust L5, L8, and L9 for maximum RF power.  
Adjust VR4 for 100% modulation.  
VR6: RF meter adjustment  
VR5: S meter adjustment  
L10: TVI trap adjustment

AUDIOVOX MCB750

Adjust T7, L3, and L4 for maximum RF power.  
Adjust VR3 for 100% modulation or clip D9.  
Connect pins 9 and 10 of M20 PLL OSC unit  
together for new frequencies.

COBRA 21 GTL/ 25GTL

Adjust L10 for maximum RF power.  
Adjust VR5 for 100% modulation.  
VR3: TX power meter adjustment  
VR1: S meter adjustment

FANON FANFARE 182F

Adjust T13, L9 for maximum RF output.  
Adjust VR9 for 100% modulation.  
VR6: TX power meter adjustment  
Connect pin 8 to pin 10 of Rec86345 PLL for  
new frequencies. Connect pins 10 and 11 of PLL  
together for new frequencies.