

ALARON

Adjust VR402 for RF power meter adjustment.
Adjust L403 and L406 for maximum power.
Cut D207 for 100% modulation.
Connect pin 2 of IC1 to 6.24V source for more frequencies.

BOMAN CB950

Adjust VR4 for maximum AM power.
Adjust RV 2 for maximum SSB power.
Adjust RV 12 for 100% modulation.
RV3: RF panel meter adjustment.

COURIER CLASSIC PLI40

Adjust L903, and L906 for maximum power.
Adjust VR6 for 100% modulation.
VR7: RF panel meter adjustment.

COBRA 46XLR

Adjust L109 for maximum power.
Adjust VR105 for 100% modulation.
VR104; RF panel meter adjustment.

COBRA 50XLR

Adjust VR5 for 100% modulation.

COBRA 55XLR

Adjust VR5 for 100% modulation.

COURIER FANON ROGUE 40 and FANFARE 125F

Adjust T14, T13, and L9 for maximum power.
Adjust VR5 for 100% modulation.
Adjust T12 for minimum interference to TV to 54 mhz harmonic.
VR6: RF panel meter adjustment.
Connect pin 10 Of U1 to 4.83V source and connect pin 11 of U1 to 4.83V source for more frequencies.