



With DPDT switch in off position, radio operates on normal 40 channels. Refer to Volume 6, Page 27 for frequency chart.

Position: *	1. 26.325-26.545	4. 26.875-26.960
	2. 26.555-26.640	5. 27.425-27.595
	3. 26.645-26.865	6. 27.605-28.045

THIS MOD WORKS

Q303 AMC

If you use the CB/PA switch: Do AS follows

1. UNPLUG Yellow wire of CB/PA from P30 ON PCB AND SOLDER TO GRD.
2. UNPLUG BLACK WIRE OF CB/PA from PA JACK BOARD NEXT TO DC PWR PLUG AND SOLDER TO (A)
3. UNPLUG ORANGE wire OF CB/PA from P27 ON PCB AND SOLDER TO P8 of IC 701
4. UNPLUG RED<sup>(-)</sup> wire of CB/PA from P28 ON PCB
5. UNPLUG RED<sup>(+)</sup> wire of CB/PA from P29 ON PCB AND SOLDER TO (B) OF ROTARY switch
6. ON PCB short P28 TO P29
- 7.