

SPECIFIC RADIO TUNE-UPS (Cont'd):

SBE LCMS-8 (MB8719):

Use Master Modification as shown in Volume 10 Page 25.

SBE Land Command LCB-8 UPD2816C:

RX: VR1; If Gain.
VR3; Squelch Range.
VR2; S Meter.

TX: Peak L17, L16, and L13. L10 is T.V.I. Filter.
VR6; AMC or Clip D16.
VR4; RF Power Meter.
VR5; Mod. Meter.

Zapper will install @ C79 for extra Channels.

Sharp CB2170 TC9102P:

RX: R709; Squelch Range.
R32; S Meter.

TX: Peak T301, T302, T303, T304, L302, and L301.
R110 AMC
R315; RF Power Meter.

Zapper installs @ C210 for extra frequency.
T202; VCO Coil.

Sharp CB4370:

RX: R709; Squelch Range
R32; S Meter

TX: Peak T301, T302, T303, T304, L302 and L301.
R110; AMC
R315; RF Power Meter.
L304; T.V.I. Filter (54MHz).
L303; 3rd Harmonic Filter (81MHz).