

## SCANNER TRICKS

"Reprinted by permission of LESCO"

### REGENCY ACT-16K: Frequency Limits Removal

1. Touch "MA"
2. Touch "9"
3. Touch "CL"
4. This removes frequency limits.

#### Frequency Limits Re-entered

1. Touch "MA"
2. Touch "9"
3. Touch "."
4. Frequency limit back in.

### BEARCAT 220: OUT OF BAND SEARCH - All 3 bands.....

#### 50-118MHz Range

1. Manually select Channel 2. Enter "50.000"
  2. Select channel 1 in manual mode.
  3. Enter "50.000" and press "Limit".
  4. Step to channel 2, and enter "118.000" and press "Limit".
  5. Press "Search". The unit will display "Error".
  6. Press "Limit" again.
  7. Press "Search".
- Unit will now be searching from 50-118MHz.  
Press "Scan" to resume normal functions.

#### 136-144MHz Range

1. Manually select Channel 2. Enter "136.000".
  2. Select Channel 1 in manual mode.
  3. Enter "136.000" and press "Limit".
  4. Step to Channel 2 and enter "144.000" and press "Limit".
  5. Press "Search". The unit will display "Error".
  6. Press "Limit" again.
  7. Press "Search".
- Unit will now be searching from 136-144MHz.  
Press "Scan" to resume normal functions.

#### 174-420.5MHz Range

1. Manually select Channel 2. Enter "174.000".
  2. Select Channel 1 in manual mode.
  3. Enter "174.000" and press "Limit".
  4. Step to Channel 2 and enter "420.500" and press "Limit".
  5. Press "Search". The unit will display "Error".
  6. Press "Limit" again.
  7. Press "Search".
- Unit will now be searching from 174-420.5MHz.  
Press "Scan" to resume normal functions.