

SPECIFIC TUNE-UPS

Colt 357; (NOT A HANDGUN!); but a new 40 Channel mobile (PLL-C5121).
 Another of the new units that have push button UP/DOWN channel selection. Tune-up; RV1-RX lights, RV2-Sq Rng, RV3-AMC.
 (Defeat for AMC is C61, 3.3Mf/25V). RX: HT101, HT102, HT103, HT104, and HT105. C43, 1Mf/10V can be increased in value for NB performance gain. TX: LX18, LX19, and LX20.

ANTLAFIER

This is a 'NEW' product on the "market". Be WARNED; don't drive with over 5W ----- this includes the swing, not deadkey wattage. It has a habit of smoking if overworked. A good note however is that "source" said, "TVI was exceptional"! (Specifications and Skem. below).

SPECIFICATIONS

POWER OUTPUT:	60-80 Watts / 40-50W Optimum for best AM modulation
DRIVE POWER:	5 Watts Max / 3 Watts AM Optimum 6 Watts SSB Optimum
MODES:	AM/SSB Automatic delay for SSB
RF GAIN:	13DB Min.
EFFICENCY:	55%
DC POWER REQUIREMENT:	13.8 VDC @ 7 AMPS. 18VDC Max
FREQUENCY RANGE:	26 - 30 MHZ adjustable
MAX SWR ALLOWED	3:1

