



Figure 19 WIRING SIDE BOARD (P.W.B. NO. F0485AF-3)

NOTE:

- In case of adding ceramic filter CF-2 and CF-3. (Reference figures are 18 and 19.)
 - Add a ceramic filter CF-2 (RFILA0050AFZZ)
 - Add a ceramic filter CF-3 (RFILA0001AFZZ)
 - Change the capacitor C37 from 0.01MFD to 680PF (VCCSPUIHL681J)
 - Cut the printed circuit pattern, the place is shown on Figure 19-①.
- In case of adding ceramic filter CF-3. (Reference figures are 18 and 19)
 - Add a ceramic filter CF-3 (RFILA0001AFZZ)
 - Change the capacitor C37 from 0.01MFD to 680PF (VCCSPUIHL681J)