

Replacement Parts

NOTE: Location column pertains to grid coordinates shown in printed circuit board diagrams Figures 21 and 22 on Pages 25 and 26.

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
CAPACITORS							
C1	742688	.1 uF, 10 v, AROX (14T303 & 14T305 only)	H2	C40	742532	330 pf, 50 v, CER (Except 14T303)	A5
C1	122522	.1 uF, 10 v, Elyt. (Except 14T303 & 14T305)	H2	C40	742071	330 pf, 50 v, CER (14T303 only)	A5
C2	742072	10 uF, 16 v, Elyt.	F1	C41	742070	.01 uF, 50 v, CER	A6
C3	742553	0.22 uF, 10 v, AROX	G2	C42	426475	120 pf, 10%, 50 v, CER	B5
C4	741788	68 pf, 10%, 50 v, Ceramic	F2	C43	437367	220 pf, 5%, 50 v, Ceramic	B6
C5	742070	.01 uF, 50 v CER	F2	C44	426475	120 pf, 10%, 50 v, CER	C6
C6	741807	22 pf, 10%, 50 v Ceramic	F2	C45	742070	.01 uF, 50 v, CER	C7
C7	437367	220 pf, 5%, 50 v, Ceramic	F2	C46	426475	120 pf, 10%, 50 v, CER (Except 14T260)	A7
C8	426475	120 pf, 10%, 50 v, CER	G2	C47	741776	270 pf, 10%, 500 v, Mica (Except 14T260)	A7
C9	741779	.047 uF, 10%, 50 v, Ceramic (Except 14T303)	I2	C47	431425	120 pf, 500 v, Mica (14T260 only)	A7
C9	436354	470K pf, 10%, 50 v CER Plate (14T303 only)	I2	C48	742533	2 pf, 50 v, CER	B8
C10	742524	47 pf, 50 v, CER	H2	C49	742084	.0047 uF, 50 v, CER	B8
C11	742077	47 uF, 10 v, Elyt.	H3	C50	742076	1 uF, 50 v, Elyt. (Except 14T303)	C9
C12	742528	4 pf, 50 v, CER (Except 14T260 & 14T304)	I4	C50	137903	1 uF, 20%, 50 v, CER Plate (14T303 only)	C9
C12	742525	18 pf, 50 v, CER (14T260 & 14T304)	I4	C51	437390	27 pf, 50 v, CER	B7
C13	741754	.001 uF, 10%, 50 v, Film Mylar	H4	C52	742070	.01 uF, 50 v, CER	C4
C14	741788	68 pf, 10%, 50 v, Ceramic	G4	C53	741779	.047 uF, 10%, 50 v, Ceramic (Except 14T303)	D6
C15	742070	.01 uF, 50 v, CER	I3	C53	436354	470K pf, 10%, 50 v, CER Plate (14T303 only)	D6
C16	437381	33 pf, +50-10%, 50 v Ceramic	G3	C54	741780	.047 uF, 10%, 50 v, Film Mylar	F6
C17	741766	12 pf, 10%, 50 v, Ceramic (Except 14T303)	H3	C55	741779	.047 uF, 10%, 50 v, Ceramic (Except 14T303)	G5
C17	245245	47 pf, 5%, 75 v, CER Plate (14T303 only)	H3	C55	436354	470K pf, 10%, 50 v, CER Plate (14T303 only)	G5
C18	742076	1 uF, 50 v, Elyt. (Except 14T303)	G3	C56	742070	.01 uF, 50 v, CER	C5
C18	137903	1 uF, 20%, 50 v, CER Plate (14T303 only)	G3	C57	742069	10 pf, 50 v, CER	D4
C19	741754	.001 uF, 10%, 50 v, Film Mylar	F3	C58	742070	.01 uF, 50 v, CER	D3
C20	741754	.001 uF, 10%, 50 v, Film Mylar	H3	C59	742070	.01 uF, 50 v, CER (Except 14T304)	D2
C21	742526	100 pf, 100 v, Film-Styroflex	F3	C60	742070	.01 uF, 50 v, CER (Except 14T304)	D4
C22	423295	2 pf, 5%, 50 v, CER Disc	F4	C61	742070	.01 uF, 50 v, CER (Except 14T304)	H2
C23	742527	7 pf, 50 v, CER	D3	C62	742070	.01 uF, 50 v, CER	E4
C24	741781	33 pf, 10%, 50 v, Ceramic	F2	C63	423295	2 pf, 5%, 50 v, CER Disc	E5
C25	742528	4 pf, 50 v, CER	E2	C64	742070	.01 uF, 50 v, CER	E4
C26	742529	560 pf, 50 v, Film Styroflex (14T260 & 14T305)	E3	C65	742525	18 pf, 50 v, CER	G4
C26	742071	330 pf, 50 v, Ceramic (14T270, 14T303 & 14T304)	E3	C66	741782	2.2 pf, 10%, 500 v, Ceramic	H6
C27	742530	390 pf, 50 v, CER	E2	C67	741780	.047 uF, 10%, 50 v, Film Mylar (Except 14T260)	H5
C28	742070	.01 uF, 50 v, CER	F4	C68	741780	.047 uF, 10%, 50 v, Film Mylar (Except 14T260 & 14T304)	I6
C29	423291	68 pf, 50 v, CER	D2	C69	741780	.047 uF, 10%, 50 v, Film Mylar (Except 14T260 & 14T304)	I6
C30	742531	56 pf, 50 v, CER	F2	C70	741780	.047 uF, 10%, 50 v, Film Mylar	I6
C31	742070	.01 uF, 50 v, CER	E2	C70	742076	1 uF, 50 v, Elyt. (14T304 only)	I6
C32	423295	2 pf, 5%, 50 v, CER Disc	D2	C71	741780	.047 uF, 10%, 50 v, Film Mylar	I7
C33	742070	.01 uF, 50 v, CER	E1	C72	742068	10 uF, 16 v, Elyt.	G5
C35	437367	220 pf, 5%, 50 v, Ceramic (14T305 only)	C2	C73	741789	.022 uF, 10%, 50 v, Film Mylar (14T305 only)	I8
C35	423291	68 pf, 50 v, CER (14T260, 14T270 & 14T303)	C2	C73	742534	6800 pf, 50 v, Film, Mylar (Except 14T305)	I8
C35	742531	220 pf, 50 v, CER (14T304 only)	C2	C74	742074	3.3 uF, 25 v, Elyt. (Except 14T303)	G5
C36	742070	.01 uF, 50 v, CER (14T260, 14T270 & 14T303)	B2	C74	166477	3.3 uF, 25 v, Elyt. (14T303 only)	G5
C36	426475	120 pf, 50 v, CER (14T304 only)	B2	C75	741755	.01 uF, 10%, 50 v, Film Mylar (14T305 only)	G7
C37	741763	100 pf, 10%, 50 v, Ceramic	B2	(Continued on Page 38)			
C38	742070	.01 uF, 50 v, CER	B3				
C39	741755	.01 uF, 10%, 50 v, Film Mylar	B5				

* (See Page 45)

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
C75	742075	.0047 uF, 50 v, Film Mylar (14T303 only)	G7	C111	425839	82 pf, 50 v, CER (14T305 only)	
C75	741786	.0022 uF, 10%, 50 v, Film Mylar (Except 14T303)	G7	C111	741777	82 pf, 50 v, CER (Except 14T305)	
C76	742076	1 uF, 50 v, Elyt. (Except 14T303 & 14T304)	H9	C113	742076	1 uF, 50 v, Elyt. (Except 14T303 & 14T305)	I3
C76	137903	1 uF, 20%, 50 v, CER Plate (14T303 only)	H9	C113	137903	1 uF, 20%, 50 v, CER Plate (14T303 only)	I3
C77	423283	100 pf, 50 v, CER	F6	C114	105310	390 pf, 500 v, CER (14T303 & 14T305)	A8
C78	742079	47 uF, 16 v, Elyt.	B3	C114	427797	390 pf, 500 v, CER (14T260 only)	A8
C79	741789	.022 uF, 10%, 50 v, Film Mylar (Except 14T270 & 14T303)	I8	C114	426853	390 pf, 500 v, 5%, Mica (14T270 only)	A8
C79	437396	.022 uF, 10%, 50 v, Mylar Film (14T303 only)	I8	C114	742565	90 pf, 500 v, 10%, Ceramic (14T304 only)	A8
C80	742078	.0022 uF, 50 v, CER (Except 14T303)	E6	C117	426478	4700 pf, 10%, 50 v, CER Plate (14T303 & 14T305)	H1
C80	249942	2200 pf, 10%, 50 v, W5R, CER Plate (14T303 only)	F6	C117	432515	4700 pf, 20%, 50 v, Ceramic (14T260 & 14T304)	H1
C81	741789	.022 uF, 10%, 50 v, Film Mylar (Except 14T270 & 14T303)	F6	C117	423274	1000 pf, 50 v, Ceramic (14T270 only)	H1
C81	437396	.022 uF, 10%, 50 v, Mylar Film (14T303 only)	F6	C118	742536	.022 uF, 50 v, CER	H2
C82	437367	220 pf, 5%, 50 v Ceramic	F7	C120	742085	33 uF, 16 v, Elyt.	D1
C83	741755	.01 uF, 10%, 50 v, Film Mylar	F7	C123	437365	.068 uF, 10%, 50 v, Mylar Film (14T303 only)	I8
C84	742078	.0022 uF, 50 v, CER (Except 14T303)	F8	C130	742078	.0022 uF, 50 v, CER (14T270 & 14T305)	I4
C84	249942	2200 pf, 10%, 50 v, W5R, CER Plate (14T303 only)	F8	C130	249942	2200 pf, 10%, 50 v, W5R, CER Plate (14T303 only)	I4
C85	741793	3.9 uF, 25 v, Tantalum	G8	C131	741761	39 pf, 10%, 50 v, Ceramic	J4
C86	742584	.47 uF, 10 v, AROX (14T305 only)	E7	C132	423293	15 pf, 50 v, CER (14T305 only)	J4
C86	742535	.47 uF, 10 v, AROX (Except 14T305)	E7	C132	741810	15 pf, 10%, 50 v, Ceramic (14T270 & 14T303)	J4
C87	741794	33 uF, 6.3 v, Elyt.	F8	C133	742078	.0022 uF, 50 v, CER (14T270 & 14T305)	J4
C88	423291	68 pf, 50 v, CER	F8	C133	249942	2200 pf, 10%, 50 v, W5K, CER Plate (14T303 only)	J4
C89	423291	68 pf, 50 v, CER	F8	C134	742554	3 pf, 50 v, Ceramic	E5
C90	423283	100 pf, 50 v, CER	F8	C135	437367	220 pf, 5%, 50 v, Ceramic	D5
C91	741795	.068 uF, 10%, 50 v, Film Mylar (Except 14T303)	F8	C136	235204	3300 pf, 10%, 200 v, Y5F, CER Disc (14T303 & 14T305)	E5
C91	437365	.068 uF, 10%, 50 v, Mylar Film (14T303 only)	F8	C136	742555	3300 pf, 10%, 200 v, Y5F, CER Disc	E5
C92	423283	100 pf, 50 v, CER	F9	C137	742070	.01 uF, 50 v, CER	E5
C93	742079	47 uF, 16 v, Elyt.	E8	C138	742070	.01 uF, 50 v, CER	F5
C94	741797	220 uF, 16 v, Elyt.	E9	C139	437367	220 pf, 5%, 50 v, Ceramic	E5
C95	741795	.068 uF, 10%, 50 v, Film Mylar (Except 14T303)	F9	C141	742070	.01 uF, 50 v (14T303 & 14T305)	
C95	437365	.068 uF, 10%, 50 v, Mylar Film (14T303 only)	F9	C150	742068	10 uF, 16 v, Elyt. (14T305 only)	K6
C96	742074	3.3 uF, 25 v, Elyt. (Except 14T303)	D7	C151	122727	47 uF, 6.3 v, Elect (14T305 only)	K3
C96	166477	3.3 uF, 25 v, Elyt. (14T303 only)	D7	C152	742688	.1 uF, 10 v, AROX (14T305 only)	I3
C97	742077	47 uF, 10 v, Elyt.	E6	C153	742688	.1 uF, 10 v, AROX (14T305 only)	I3
C99	742081	47 uF, 25 v, Elyt.	C8	C154	742688	.1 uF, 10 v, AROX (14T305 only)	I3
C100	742080	1000 uF, 16 v, Elyt. (Except 14T303)	E8	C155	742578	.047 uF, 125 v, Variable (14T305 only)	J3
C100	740844	1000 uF, 16 v, Elyt. (14T303 only)	E8	C156	742578	.047 uF, 125 v, Variable (14T305 only)	J3
C101	741794	33 uF, 6.3 v, Elyt.	G8	C201A	742088	180 pf, 500 v, Mica (Except 14T303)	SWR
C102	742070	.01 uF, 50 v, CER	B1	C201	230245	150 pf, 5%, 500 v, Mica (14T303 only)	
C106	741779	.047 uF, 10%, 50 v, Ceramic (Except 14T303)	D8	C201B	742499	7 pf, 500 v, CER	RP
C106	436354	470K pf, 10%, 50 v, CER Plate (14T303 only)	D8	C202	742087	.01 uF, 50 v, CER (Except 14T260)	†
C107	741779	.047 uF, 10%, 50 v, Ceramic (Except 14T303)	A1	C202	742569	.047 uF, 50 v, CER (14T260 only)	†
C107	436354	470K pf, 10%, 50 v, CER Plate (14T303 only)	D8	C203	742087	.01 uF, 50 v, CER	†
C110	742570	18 pf, 50 v, CER	G4	C204	742087	.01 uF, 50 v, CER	†
				C205	742569	.047 uF, 50 v, CER (Except 14T260 & 14T270)	†
				C205	742087	.01 uF, 50 v, CER (14T260 & 14T270)	†
				C206	742087	.01 uF, 50 v, CER	RP
				C207	742087	.01 uF, 50 v, CER	RD
				C208	742084	.0047 uF, 50 v, CER	RP

(Continued on Page 39)

RP• On rear panel

SWR• On SWR board

†• Connected between chassis and case

* (See Page 45)

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
C209	742084	.0047 uF, 50 v, CER	RP	D22	741741	Diode - Type 1S1555 (Except 14T270)	H2
C210	742084	.0047 uF, 50 v, CER	RP	D25	741738	Diode - Type ZM2205 (14T305 only)	K6
C211	742084	.0047 uF, 50 v, CER (Except 14T305)	FP	D26	741741	Diode - Type 1S1555 (14T305 only)	K6
C212	742084	.0047 uF, 50 v, CER (Except 14T305)	FP	D27	741741	Diode - Type 1S1555 (14T305 only)	K2
C213	742084	.0047 uF, 50 v, CER (14T303 only)	FP	D28	741741	Diode - Type 1S1555 (14T305 only)	K2
C214	742084	.0047 uF, 50 v, CER (14T303 only)	FP	D29	741741	Diode - Type 1S1555 (14T305 only)	K1
C251	742070	.01 uF, 50 v, CER (14T304 only)	LC1	D30	741741	Diode - Type 1S1555 (14T305 only)	K1
C501	426027	10,000 pf, 20%, 50 v, CER Disc (14T303 & 14T305)	SWR	D33	741741	Diode - Type 1S1555 (14T305)	
C501	742557	10,000 pf, 20%, 50 v, CER Disc (14T270 only)	SWR	D501	112524	Diode - Type 1N60 (14T270 & 14T305)	SWR
C502	426027	10,000 pf, 20%, 50 v, CER Disc (14T303 & 14T305)	SWR	D501	112524	Diode - Type 1N60 (14T303)	SWR
C502	742557	10,000 pf, 20%, 50 v, CER Disc (14T270 only)	SWR	D502	112524	Diode - Type 1N60 (14T303)	SWR
C503	426027	10,000 pf, 20%, 50 v, CER Disc (14T305 only)	SWR	D502	112524	Diode - Type 1N60 (14T270 & 14T305)	SWR
C541	742084	.0047 uF, 50 v, CER (14T303 only)	SWR	D541	112524	Diode - Type 1N60 (14T303)	SWR
C542	436354	0.47 uF, 50 v, Electrolytic (14T303 only)	SWR	D542	112524	Diode - Type 1N60 (14T303)	SWR
C543	742084	.0047 uF, 50 v, CER (14T303 only)	SWR	IC1	741686	I.C. - Type PLL02A	I2
C544	742084	.0047 uF, 50 v, CER (14T303 only)	SWR	IC2	742510	I.C. - Type TA731P	G3
C951	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	IC3	742510	I.C. - Type TA731P	E2
C952	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	IC4	741687	I.C. - Type TA7205P	F8
C953	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	IC5	742619	I.C. - Type C1004T (14T305 only)	J3
C954	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	J1	742497	Connector - Jack, Ant	H3
C955	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	J1	742665	Connector - Jack, Ant (14T303 only)	H3
C956	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	J2	741815	Connector - Jack, Microphone (Except 14T305)	I3
C957	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	J3	742498	Connector - Jack, Ext, SP	I3
C958	742084	.0047 uF, 50 v, CER (14T305 only)	MRB	J4	742498	Connector - Jack, Ext, SP	H1
CF1	741812	Filter, CER	H5	J5	741819	Connector - Jack, D.C. (Except 14T260 & 14T303)	RP
CH1	741691	Coil, Choke	B1	J7	742666	Connector - Jack, Phone (14T303 only)	H4
CR1	742591	Module (14T303 only)		J951	742667	Connector - Jack, Mic (14T305 only)	MRB
CT1	741721	Capacitor, Trimmer	J4	L1	742514	Coil - RF	F2
D1	741689	Diode - Type ITT410	F2	L2	741720	I.F. , T	F2
D2	741738	Diode - Type ZM2205	G3	L3	741697	Coil - R.F.	G3
D3	741739	Diode - Type RD9.1E	B4	L4	742515	Coil - Peaking, 1 UH	D3
D4	741741	Diode - Type 1S1555	D4	L5	742516	Coil - RF-27, MHZ	E1
D5	112524	Diode - Type Special	BA	L6	741695	Coil - R.F.	A6
D6	741741	Diode - Type 1S1555	C6	L7	741696	Coil - R.F.	B5
D7	741741	Diode - Type 1S1555	C7	L8	741697	Coil - R.F.	B6
D8	112524	Diode - Type Special	I8	L9	741703	Coil - R.F.	B7
D9	112524	Diode - Type Special	H8	L10	741698	Coil - R.F.	B7
D10	741741	Diode - Type 1S1555 (Except 14T305)	H7	L11	741699	Coil - R.F.	A7
D11	741741	Diode - Type 1S1555 (Except 14T260 & 14T305)	D6	L12	741700	Coil - R.F.	B8
D12	741741	Diode - Type 1S1555 (Except 14T304)	D6	L13	742517	Coil - R.F.	A9
D13	166593	Diode - Type V06C	C7	L14	742521	Coil - R.F. (Except 14T260)	E4
D14	741740	Diode - Type 1S1885	A2	L14	742551	Coil - R.F. (14T260 only)	E4
D15	741741	Diode - Type 1S1555 (14T260) R111 47 ohms on 14T303	I3	L15	741697	Coil - R.F.	B3
D16	741741	Diode - Type 1S1555 (Except 14T270)	C3	L16	741702	Coil - R.F.	B1
D17	741741	Diode - Type 1S1555 (Except 14T260 & 14T304)	F6	L17	741702	Coil - R.F.	A3
D18	112524	Diode - Type Special (Except 14T260 & 14T304)	D6	L201	742605	Coil (14T303 only)	
D19	112524	Diode - Type Special (Except 14T260 & 14T304)	D5	LED	742618	Diode - Type SL122, LED (14T304 & 14T305)	FP
				LED301	742568	Diode - Type SL122	FP
				M	741831	Meter - D.C. with Lamp (14T270 & 14T305)	FP

(Continued on Page 40)

FP• On front panel

MRB• On microphone rec. board

RP• On rear panel

SWR• On SWR board

* (See Page 45)

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
M	741846	Meter - D.C. (14T260 only)	FP	Q251	742567	Transistor - Type 2SC1383 (14T304 only)	LCI
M	742560	Meter (14T304 only)	FP	Q501	112524	Diode - Type 1N60 (14T303 only)	SWR
M1	742675	Meter - S/MOD (14T303 only)	FP	Q502	112524	Diode - Type 1N60 (14T303 only)	SWR
M2	742677	Meter - RF/CAL/SWR (14T303 only)	FP	Q541	742703	Transistor - Type 2SC945AP (14T303 only)	SWR
PL1	741818	Lamp - Pilot (14T260 & 14T270)	FP	Q541	112524	Diode - Type 1N60 (14T303 only)	SWR
PL1	742679	Lamp (14T303 only)	FP	Q542	112524	Diode - Type 1N60 (14T303 only)	SWR
PL1	742561	Lamp (14T304 only)	FP	Q801	742558	Transistor - Type 2SC945RQ (14T270 only)	LB
PL2	741833	Lamp - Pilot (14T305 only)	FP	Q802	742558	Transistor - Type 2SC945RQ (14T270 only)	LB
PL2	741818	Lamp - Pilot (14T260 only)	FP				
PL2	741832	Lamp - Pilot (14T270 only)	FP				
PL2	742679	Lamp (14T303 only)	FP				
PL3	741818	Lamp - Pilot (14T260 only)	FP				
PL3	742678	Lamp (14T303 only)	FP				
PL4	74254	Lamp (14T303 only)	FP				
PT	742648	Transformer (14T303 only)					
Q1	742544	Transistor - Type 2SC710DE (Except 14T303)	I4	R1	107972	3300 Ohm, 5%, 1/4 w, Comp	H2
Q1	742624	Transistor - Type 2SD313 (14T303 only)	I4	R2	108864	470 Ohm, 5%, 1/4 w, Comp	F1
Q2	742544	Transistor - Type 2SC710DE	H2	R3	426112	22000 Ohm, 5%, 1/4 w, Comp	G1
Q3	741731	Transistor - Type 2SC1687	B2	R4	108871	47000 Ohm, 1/4 w, Comp (Except 14T260)	F1
Q4	742537	Transistor - Type 2SC1360 (Except 14T270)	A5	R5	426216	68 Ohm, 5%, 1/4 w, Comp (14T303 & 14T305)	F4
Q4	742545	Transistor - Type 2SC1846 QRS (14T270 only)	A5	R5	108861	100 Ohms, 5%, (14T260 & 14T270)	F4
Q5	741732	Transistor - Type 2SC1306 (Except 14T260)	B6	R6	426215	680 Ohms, 1/4 w, 5%, Comp	H3
Q5	742511	Transistor - Type 2SC1360 (14T260 only)	B6	R7	219467	27000 Ohm, 5%, 1/4 w, Comp	I4
Q6	741856	Transistor - Type 2SC1318	C3	R8	108869	15000 Ohm, 5%, 1/4 w, Comp	H4
Q7	742546	Transistor - Type 2SA719PQR	C3	R9	219459	1500 Ohm, 5%, 1/4 w, Comp	G4
Q8	742547	Transistor - Type 2SA1047BC (Except 14T303)	C5	R11	227959	82 Ohm, 5%, 1/4 w, Comp	G3
Q8	742622	Transistor - Type 2SC1047BCC (14T303 only)	C5	R12	108866	2200 Ohm, 5%, 1/4 w, Comp	G3
Q9	742548	Transistor - Type 2SC1359BC	D5	R13	227744	150 Ohm, 5%, 1/4 w, Comp	F3
Q10	741726	Transistor - Type 2SC710D	G4	R14	218762	1000000 Ohm, 5%, 1/4 w Comp	G1
Q11	741726	Transistor - Type 2SC710D	H6	R15	108860	47 Ohm, 5%, 1/4 w, Comp	D2
Q12	742549	Transistor - Type 2SC829BC	J6	R16	108861	100 Ohm, 5%, 1/4 w, Comp	E1
Q13	741737	Transistor - Type 2SC828P	G8	R17	108869	15000 Ohm, 5%, 1/4 w, Comp (14T304 & 14T305)	D2
Q14	741729	Transistor - Type 2SA719Q	D7	R17	239954	5600 Ohms, 2%, 1/4 w, Film (Except 14T304 & 14T305)	D2
Q15	742512	Transistor - Type 2SC945(L)PO	E7	R18	426216	68 Ohm, 5%, 1/4 w, Comp	B2
Q16	742544	Transistor - Type 2SC710DE (Except 14T260 & 14T304)	J4	R19	108861	100 Ohm, 5%, 1/4 w, Comp	B5
Q17	742544	Transistor - Type 2SC710DE (Except 14T260 & 14T304)	J4	R20	218758	220 Ohm, 5%, 1/4 w, Comp (Except 14T260)	A6
Q18	166906	Transistor - Type 2SC829C (14T270 & 14T303)	D5	R21	135726	10 Ohms, 5%, 1/4 w, Film (14T303 & 14T305)	B7
Q19	742008	Transistor - Type 2SA733P.Q. (Except 14T260 & 14T304)	F5	R21	239417	10 Ohms, 5%, 1/2 w, Film - Metal Oxide (14T260, 14T270 & 14304)	B7
Q20	742550	Transistor - Type 2SC1327T.U (Except 14T260 & 14T304)	G5	R22	426216	68 Ohm, 5%, 1/4 w, Comp	B6
Q21	742558	Transistor - Type 2SC945RQ (14T303 & 14T305 only)	J5	R23	108871	47000 Ohm, 5%, 1/4 w, Comp (Except 14T260)	B9
Q22	742513	Transistor - Type 2SC900U	G1	R23	742522	57K Ohms (14T260 only)	B9
Q25	742623	Transistor - Type 2SC1096-3SL (14T305 only)	K5	R24	426215	680 Ohms, 1/4 w, 5%, Comp	B8
Q26	742621	Transistor - Type 2SC735GR (14T305 only)	K5	R25	219458	330 Ohms, 5%, 1/4 w, Comp	C6
Q27	742621	Transistor - Type 2SC735GR (14T305 only)	K4	R26	108865	1000 Ohm, 5%, 1/4 w, Comp (Except 14T260)	C4
				R27	426215	680 Ohms, 1/4 w, 5%, Comp	C5
				R28	108871	47000 Ohm, 5%, 1/4 w, Comp	C4
				R29	107972	3300 Ohm, 5%, 1/4 w, Comp	B4
				R30	108861	100 Ohm, 5%, 1/4 w, Comp	C5
				R31	219460	1800 Ohm, 5%, 1/4 w, Comp	D4
				R32	227741	560 Ohm, 5%, 1/4 w, Comp	E4

(Continued on Page 41)

FP• On front panel

LB• On lamp board

LCI• On LED chan. ind. board

SWR• On SWR board

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCA-TION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCA-TION
R33	108864	470 Ohm, 5%, 1/4 w, Comp	F5	R77	133240	270 Ohms, 2%, 1/2 w, Film (14T260 only)	J4
R34	232389	470000 Ohm, 5%, 1/4 w, Comp	G4	R77	742015	150 Ohms, 1W, Film-Metal Oxide (14T270 only)	J4
R35	108865	1000 Ohm, 5%, 1/4 w, Comp	H5	R77	435050	150 Ohms, 1%, 1 w, Film (14T304 only)	J4
R36	426213	4700 Ohm, 5%, 1/4 w, Comp	H6	R78	742643	15 Ohm, 5%, 2 w, Film (14T305 only)	
R37	108864	470 Ohm, 5%, 1/4 w, Comp	I5	R78	742552	15 Ohms, 2 w, Film-Metal Oxide (Except 14T305)	
R38	108871	47000 Ohm, 5%, 1/4 w, Comp	H6	R79	426112	22K Ohms, 5% (14T304 only)	F4
R39	218758	220 Ohm, 5%, 1/4 w, Comp	I6	R80	108867	6800 Ohm, 5%, 1/4 w, Comp	
R40	427563	3900 Ohm, 5%, 1/4 w, Comp	I7	R81	133240	270 Ohms, 2%, 1/2 w, Film (14T260 & 14T303 only)	J5
R41	108869	15000 Ohm, 5%, 1/4 w, Comp	I6	R82	426213	4700 Ohms, 5%, (14T303 only)	
R42	426219	33000 Ohm, 5%, 1/4 w, Comp	H6	R84	108869	15000 Ohm, 5%, 1/4 w, Comp (14T305 only)	J6
R43	218758	220 Ohm, 5%, 1/4 w, Comp	I5	R84	218499	10K Ohms, 5% (14T303 only)	J6
R44	108860	47 Ohm, 5%, 1/4 w, Comp	I7	R85	133240	270 Ohms, 2%, 1/2 w, Film (14T303 only)	J6
R45	426112	22000 Ohm, 5%, 1/4 w, Comp	H7	R85	741725	330 Ohm, 1/2 w, Film Metal Oxide (14T305 only)	J6
R46	232687	270000 Ohm, 5%, 1/4 w, Comp (Except 14T303 & 14T304)	H7	R86	107972	3300 Ohm, 5%, 1/4 w, Comp (14T303 & 14T305)	H5
R47	108871	47000 Ohm, 5%, 1/4 w, Comp	H8	R86	219465	8200 Ohms, 5% (14T270 only)	H5
R48	427566	68,000 Ohm, 1/4 w, 5%, Comp	H8	R87	107972	3300 Ohm, 5%, 1/4 w, Comp (14T270 & 14T305)	I5
R49	426219	33000 Ohm, 5%, 1/4 w, Comp	H8	R88	218499	10000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	J4
R50	108871	47000 Ohm, 5%, 1/4 w, Comp	H8	R89	218499	10000 Ohm, 5%, 1/4 w, Comp (14T270, 14T303 & 14T305)	J3
R51	218499	10000 Ohm, 5%, 1/4 w, Comp	G9	R90	223769	100000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	
R52	135726	10 Ohms, 5%, 1/4 w, Film (Except 14T260 & 14T304)	B3	R91	108865	1000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	
R52	239417	10 Ohms, 5%, 1/2 w, Film-Metal Oxide (14T260 & 14T304)	B3	R92	241991	560,000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	F5
R53	108865	1000 Ohm, 5%, 1/4 w, Comp	C3	R93	223769	100000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	E6
R54	433018	390 Ohms, 5%, 1/4 w, Comp	D3	R94	243304	820,000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	F5
R55	218499	10000 Ohm, 5%, 1/4 w, Comp	D3	R95	426213	4700 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	F5
R56	426234	820 Ohms, 10%, 1/4 w, Fixed Comp	I8	R96	426112	22000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	F5
R57	219467	27K Ohms, 5%, (Except 14T305)	E6	R98	219459	1500 Ohms, 5%, (14T303 only)	
R58	239954	5600 Ohm, 2%, 1/4 w, Film (Except 14T260 & 14T305)	G6	R99	218499	10000 Ohm, 5%, 1/4 w, Comp (14T305 only)	G5
R58	108870	18000 Ohms, 5% (14T305 only)	G6	R100	107972	3300 Ohm, 5%, 1/4 w, Comp (14T305 only)	G7
R59	107972	3300 Ohm, 5%, 1/4 w, Comp	F7	R101	742627	.47 Ohm, 5%, 1 w, Film (14T305 only)	K6
R60	108866	2200 Ohms, 5% (Except 14T305)	G8	R102	108865	1000 Ohm, 5%, 1/4 w, Comp (14T305 only)	K6
R61	426234	820 Ohms, 10%, 1/4 w, Fixed Comp	G8	R103	107972	3300 Ohm, 5%, 1/4 w, Comp (14T305 only)	K5
R62	108860	47 Ohm, 5%, 1/4 w, Comp	G9	R104	107972	3300 Ohm, 5%, 1/4 w, Comp (14T305 only)	K3
R63	218499	10000 Ohm, 5%, 1/4 w, Comp	G8	R105	108861	100 Ohm, 5%, 1/4 w, Comp (14T305 only)	J1
R64	108860	47 Ohm, 5%, 1/4 w, Comp	D6	R106	108861	100 Ohm, 5%, 1/4 w, Comp (14T305 only)	J1
R65	108865	1000 Ohm, 5%, 1/4 w, Comp	D6				
R66	426213	4700 Ohm, 5%, 1/4 w, Comp (Except 14T303)	E7				
R66	108871	47K Ohms, 5% (14T303 only)	E7				
R67	108870	18000 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T270)	E7				
R67	426112	22K Ohms, 5% (14T260 only)	E7				
R67	219460	1800 Ohms, 5% (14T270 only)	E7				
R68	108865	1000 Ohm, 5%, 1/4 w, Comp	E7				
R69	426112	22000 Ohm, 5%, 1/4 w, Comp	H8				
R70	426112	22000 Ohm, 5%, 1/4 w, Comp (Except 14T304)	H6				
R71	219460	1800 Ohm, 5%, 1/4 w, Comp (Except 14T260)	G7				
R72	219459	1500 Ohms, 5% (Except 14T303 & 14T305)	E3				
R73	426213	4700 Ohm, 5%, 1/4 w, Comp	H7				
R74	426112	22K Ohms, 5% (14T260 only)	H7				
R75	426213	4700 Ohm, 5%, 1/4 w, Comp	D3				
R76	133240	270 Ohms, 2%, 1/2 w, Film (14T260 & 14T270 only)	J4				
R77	230014	150 Ohm, 5%, 1 w, Film (14T305 only)	J4				

(Continued on Page 42)

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
R107	223769	100000 Ohm, 5%, 1/4 w, Comp (14T305 only)	I2	S4	741817	Switch - Slide (Except 14T260)	FP
R108	426112	22000 Ohm, 5%, 1/4 w, Comp (14T305 only)	I3	S5	741817	Switch - Slide (Except 14T260 & 14T304)	FP
R111	113524	2700 Ohms, 5% (14T303 only)	J8	S6	742645	Switch (14T305 only)	FP
R112	219467	27000 Ohm, 5%, 1/4 w, Comp (14T305 only)	J9	S6 (VR2)	741834	Switch, Slide (14T270 only)	FP
R201	223769	100000 Ohm, 5%, 1/4 w, Comp		S6 (VR2)	742639	Resistor, Variable, Linear 10K Ohms & Switch (SQ/PA) (14T303 only)	FP
R202	223769	100K Ohms, 5%, (14T270 & 14T304)	FP	S7	741817	Switch, Slide (14T270 only)	FP
R203	230014	150 Ohms, 1 w, Film (14T303 only)	FP		742509	Switch, Rotary (14T260 only)	FP
R204	230014	150 Ohms, 1 w, Film (14T303 only)	FP	SP	741830	Speaker (Except 14T260 & 14T303)	CB
R251	239954	5600 Ohms (14T304 only)	LC1	SP	741845	Speaker (14T260 & 14T303)	CB
R501	227959	82 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	SWR	SW1	742571	Switch, Rotary, Channel (14T303 & 14T304)	FP
R501	259954	5600 Ohms, 1/4 w, (14T304 only)	SWR		742509	Switch, Rotary (14T260 only)	FP
R502	227959	82 Ohm, 5%, 1/4 w, Comp (Except 14T260 & 14T304)	SWR	T1	742518	Transformer - R.F.	I4
R503	219460	1800 Ohm, 5%, 1/4 w, Comp (14T303 & 14T305)	SWR	T2	742519	Transformer - R.F.	E4
R503	108865	1000 Ohms, 5% (14T270 only)	SWR	T3	741712	Transformer - R.F.	C2
R541	239455	1200 Ohms, 5%, 1/4 w, Film (14T303 only)	SWR	T4	741713	Transformer - R.F.	B3
R542	218499	10K Ohms, 5% (14T303 only)	SWR	T5	741714	Transformer - R.F.	C6
R543	219459	1500 Ohms, 5% (14T303 only)	SWR	T6	742520	Transformer - R.F.	C4
R801	218499	10K Ohms, 5%, (14T270 only)	SWR	T7	742521	Transformer - R.F.	F4
R802	133240	270 Ohms, 2%, 1/2 w, Film (14T270 only)	LB	T8	741717	I.F.T. 455 KHZ	G4
R803	108869	15K Ohms, 5% (14T270 only)	LB	T9	741718	I.F.T. 455 KHZ	I6
R804	741725	330 Ohms, 1/2 w, Film-Metal Oxide (14T270 only)	LB	T10	741719	I.F.T. 455 KHZ	I7
	742566	Resistor, Array, 1800 Ohms, X7, 1/4 w (14T303)	LC	T11	741690	Transformer - A.F. Output	D8/9
	742566	Resistor, Array, 1800 Ohms, X7, 1/4 w (14T304)	K2	VR1	742637	Resistor, 1000 Ohm, Var Linear (14T305 only)	FP
	742625	Resistor, Array, 180 Ohms (14T305)	K2	VR1	742495	Resistor, 50K Ohm, Var, Linear (14T260 only)	FP
RV1	741707	Resistor, 10,000 Ohm, Var	G7	VR1	741828	Resistor, 10K Ohm, Var (14T270 & 14T304)	FP
RV2	742508	Resistor, 10000 Ohm, Var Linear	D7	VR1	742636	Resistor, 50K Ohm, Var, Linear-Vol (14T303 only)	FP
RV3	741709	Resistor, 20,000 Ohm, Var	I8	VR2	742638	Resistor, 10000 Ohm, Var Linear (14T305 only)	FP
RV4	741709	Resistor, 20,000 Ohm, Var (Except 14T303)	C4	VR2	742496	Resistor, 10K Ohm, Var, Linear (14T260 only)	FP
RV501	742631	Resistor, 5000 Ohm, Variable (14T303 & 14T305)	SWR	VR2	741829	Resistor, 10K Ohm, Var (14T270 & 14T304)	FP
RV501	742556	Resistor, 2000 Ohms, Variable Linear (14T270)	SWR	VR2	742639	Resistor, 10K Ohm, Var Linear-SQ/PA (14T303 only)	FP
RV502	742628	Resistor, Semi-Fixed, 20K Ohms "Power"	SWR	VR3	741829	Resistor, 10000 Ohm, Var Linear (14T270 & 14T305)	FP
RV541	742635	Resistor, Semi-Fixed, 20K Ohms "Mod"	SWR	VR3	741844	Resistor, 100K Ohm, Var (14T260 & 14T303)	FP
S1 (VR1)	742637	Resistor, 1000 Ohm, Var Linear Switch (14T305 only)	FP	VR3	742559	Resistor, 20K Ohm, Var, Linear (14T304 only)	FP
S1 (VR1)	742495	Resistor, 50K Ohms, Var Linear Switch (14T260 only)	FP	VR4	741843	Resistor, 10K Ohm, Var, Linear-SWR (14T303 only)	FP
S1 (VR1)	741828	Resistor, 50K Ohms, Var & Switch (14T270 only)	FP	VR4	742559	Resistor, 20K Ohm, Var, Linear (14T304 only)	FP
S2	741817	Switch, Slide (14T304 only)	FP	X1	742506	Crystal - 10.24000 MHZ	I5
S2	741834	Switch, Slide (14T270 only)	FP	X2	742507	Crystal - 10.69500 MHZ	E3
S2	742645	Switch (14T303 & 14T305)	FP				
S3	741817	Switch - Slide (Except 14T260)	FP				

(Continued on Page 43)

CB• On bottom of case

FP• On front panel

LB• On lamp board

SWR• On SWR board

* (See Page 45)

SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION	SYMB. NO.	STOCK NO.	DESCRIPTION	LOCATION
		A.C. POWER SUPPLY PW BOARD ASSEMBLY (MODEL 14T303 ONLY)		29	742505	Terminal - DC	RP
					742009	Bracket - Mobile MTG	
					741827	Cord - Pwr D.C.	
					426968	Fuse - 2 Amp 250 v	
					741825	Holder - Microphone	
					741745	Insulator Mylar Sheet (IC4)	
					741826	Microphone - CB	
					741813	Spacer Crystal	
						MECHANICAL PARTS - 14T270 (Refer to exploded view Figure 12 on Page 15)	
C1	742697	2200 uF, 25 v, Elyt	PS				
C2	436943	100 uF, 25 v, Elect	PS				
C3	422976	22,000 pf, 20%, 25 v, CER, Disc	PS				
C4	741840	.01 uF, 10%, 50 v, Ceramic	PS				
C5	429691	47000 pf, 10%, 50 v, Cer Plate	PS				
C6	422976	22,000 pf, 20%, 25 v, Cer Disc	PS				
D1	166593	Diode - Type V06C	PS				
D2	166593	Diode - Type V06C	PS				
D3	166593	Diode - Type V06C	PS				
D4	166593	Diode - Type V06C	PS				
ZD1	742692	Diode - Type BZ162	PS	1	742539	Panel - Front	FP
ZD2	742693	Diode - Type RD5.6EC	PS	2	741824	Holder - Lamp CH/TX	FP
				3	741818	Lamp - Pilot	FP
				4	741833	Lamp - Pilot	FP
F1	742695	Fuse, 2.2 Amp, 250 v	PS	5	741832	Lamp - Pilot	FP
				6	741834	Switch - Slide (Tune, SWR/CAL)	FP
Q1	126334	Transistor - Type 2SC900F	PS	7	741817	Switch - Slide	FP
Q2	126334	Transistor - Type 2SC900F	PS	8	741828	50,000 Ohm - Var	FP
				9	741829	10,000 Ohm - Var	FP
R1	502122	220 Ohms, 5%, 1/2 w, Comp	PS	10	741829	10,000 Ohm - Var	FP
R2	502047	47 Ohms, 5%, 1/2 w, Comp	PS	11	741831	Meter - D.C. with Lamp	FP
R3	427333	100 Ohms, 1/2 w, 2%, Film	PS	12	742014	Bracket - Meter Mtg	FP
R4	426742	820 Ohms, 1/2 w, 2%, Film	PS	16	741815	Connector - Jack Microphone	SP
R5	502212	1200 Ohms, 5%, 1/2 w, Comp	PS	17	742498	Connector - Jack Ext SP	RP
R6	426742	820 Ohms, 1/2 w, 2%, Film	PS	20	741819	Connector - Jack D.C.	RP
				21	742497	Connector - Jack - ANT	RP
RV1	742694	Resistor, Semi-Fixed, 500B	PS	22	742505	Terminal - D.C.	RP
	742696	Fuse Cover	PS	25	742538	Escutcheon Assembly	FP
				26	742011	Washer - Buffer Channel Plate	FP
				27	742503	Plate - Channel Indication	FP
				28	742542	Knob Assembly - Channel	FP
				29	741823	Knob - VR	FP
				32	741830	Speaker	CB
				33	742013	Bracket - Speaker MTG	CB
				34	742541	Terminal - Mike	SP
					742018	Bracket - Mobile MTG	
1	742502	Panel - Front	FP		741827	Cord - Pwr, D.C.	
2	741824	Holder - Lamp, CH/TX	FP		426968	Fuse - 2 Amp, 250 v	
3	741818	Lamp - Pilot	FP		741825	Holder - Microphone	
4	741817	Switch - Slide	FP		741745	Insulator, Mylar Sheet (IC4)	
5	741844	100,000 Ohm - Var	FP		741826	Microphone - CB	
6	742495	50000 Ohm, Var, Linear	FP		741813	Spacer, Crystal	
7	742496	10000 Ohm, Var, Linear	FP		742543	Switch - Rotary/Channel Splect	
8	741846	Meter - D.C.	FP				
9	742012	Bracket - Meter, Mtg	FP				
10	741851	Holder - Lamp	FP				
12	741815	Connector - Jack Microphone	SP				
13	742498	Connector - Jack Ext SP	RP				
16	741819	Connector - Jack D.C.	RP				
17	742497	Connector - Jack - Ant	RP				
19	742500	Escutcheon Assem	FP				
20	742011	Washer - Buffer Channel Plate	FP				
21	742503	Plate - Channel Indication	FP	1	742681	Panel - Front	FP
22	742542	Knob Assem. - CH	FP	2	741845	Speaker	FP
23	741823	Knob - VR	FP	3	742682	Bracket	FP
26	741845	Speaker	CB	4	742636	Resistor Variable Linear 50K VOL	FP
27	742013	Bracket - Speaker MTG	CB	5	742639	Resistor Variable Linear 10K SQ/PA	FP
28	742504	Washer - Mike Jack	SP	6	741844	Resistor Variable Linear 100K RF	FP
						MECHANICAL PARTS - 14T303 (Refer to exploded view Figure 13 on Page 16)	
						(Continued on Page 44)	

CB• On bottom of case FP• On front panel PS• On power supply board (14T303) RP• On rear panel SP• On side panel

PRODUCTION CHANGES

The listings given below show components which were changed during production. Over each column is given the serial numbers of the units in which the particular values appear.

14T303

Serial Nos. 16000001 to 16008000

Serial Nos. 16008001 and above

SYMB. NO.	STOCK NO.	DESCRIPTION	SYMB. NO.	STOCK NO.	DESCRIPTION
		CAPACITORS			CAPACITORS
C7	437367	220 pf, 5%, 50 v, Ceramic	C7	742071	330 pf, 50 v, Ceramic
C8	426475	120 pf, 10%, 50 v, Ceramic	C8	427831	150 pf, 10%, 50 v, Ceramic
C16	437381	33 pf, +50-10%, 50 v, Ceramic	C16	-	Not used
C113	137903	1 uF, 20%, 50 v, CER	C113	742070	.01 uF, 50 v
R72	-	-	D5	741741	Diode Type 1S1555 (Replaces R72)
R111	108860	47 ohms, 5%, 1/4 w, Comp.	R111	113524	2700 ohms, 5%, 1/4 w

14T304

Serial Nos. 17000001 to 17010000

Serial Nos. 1701001 and above

SYMB. NO.	STOCK NO.	DESCRIPTION	SYMB. NO.	STOCK NO.	DESCRIPTION
		CAPACITORS			CAPACITORS
C7	437367	220 pf, 5%, 50 v, Ceramic	C7	742071	330 pf, 50 v, Ceramic
C8	426475	120 pf, 10%, 50 v, Ceramic	C8	427831	150 pf, 10%, 50 v, Ceramic
C16	437381	33 pf, +50-10%, 50 v, Ceramic	C16	-	Not used
C17	741766	12 pf, 10%, 50 v, Ceramic	C17	245245	47 pf, 5%, 75 v
C35	742531	220 pf, 50 v, CER	C35	423291	68 pf, 50 v, CER
C40	742532	330 pf, 50 v, CER	C40	742530	390 pf, 50 v, CER
C75	741786	.0022 uF, 10%, 50 v, Mylar	C75	742075	0047 uF, 50 v, Mylar
C113	742076	1 uF, 50 v, Elyt.	C113	742070	.01 uF, 50 v
C141	-	-	C141	742070	.01 uF, 50 v
C201A	742088	180 pf, 500 v, Mica	C201A	230245	150 pf, 5%, 500 v, Mica

14T305

Serial Nos. 15000001 to 15010000

Serial Nos. 15010001 and above

SYMB. NO.	STOCK NO.	DESCRIPTION	SYMB. NO.	STOCK NO.	DESCRIPTION
		CAPACITORS			CAPACITORS
C7	437367	220 pf, 5%, 50 v, Ceramic	C7	742071	330 pf, 50 v, Ceramic
C8	426475	120 pf, 10%, 50 v, Ceramic	C8	427831	150 pf, 10%, 50 v, Ceramic
C16	437381	33 pf, +50-10%, 50 v, Ceramic	C16	-	Not used
C17	741766	12 pf, 10%, 50 v, Ceramic	C17	245245	47 pf, 5%, 75 v
C26	742529	560 pf, 50 v, Film	C26	742071	330 pf, 50 v, Ceramic
C40	742532	330 pf, 50 v, Ceramic	C40	742530	390 pf, 50 v, Ceramic
C142	-	Not used	C142	423283	100 pf, 50 v, Ceramic
C201A	742088	180 pf, 500 v, Mica	C201A	230245	150 pf, 5%, 500 v, Mica