

This mod works

CLARIFIER MODIFICATION SEARS 934.38260700

1. Locate HP2-3 connector. Cut the ^{Red}wire that goes over to one end of the Fine Tune control. Resolder this wire to pin 3 of IC502 voltage regulator so the fine tune control is fed with a steady 8 volt source.
2. Connect the other end of the Fine tune control to ground by shorting out R711. Solder BLUE WIRE TO GND.
3. Cut one end of R702 loose. ^{Located in CRYSTAL CAN}
4. Replace D702 with a Super Clarifier Diode for more slide.
NORMAL 3KC

For frequency expansion, use the standard SM5104G mod. as in Volume 6, pages 26 & 27 for this set.

