This Manual is provided by



Someone who wanted to help you repair your equipment scanned this manual.

If you would like to help us put more manuals online support us.

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. to pay my costs. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners. This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

Thank you for any support you can give.

A communication of vital interest to every Courier dealer

S-225

December 6, 1973

SUBJECT:

CAP FREQUENCIES FOR COURIER TUBE AND TRANSISTOR

UNITS (TRAVELLER AND CLASSIC)

To convert to CAP (Civil Air Patrol) frequency 26.620 mhz, remove the 37.600 mhz crystal which affects channels #1 thru #4. Substitute 37.225 crystal for CAP frequency of 26.620 to appear on the #1 position of the channel selector switch. CB channels #2-3-4 will be deleted by this change.

SUBJECT:

COURIER CLASSIC

To prevent pulses from switching of Classic on-off switch from entering the 12 volt line to the Q-10 and Q-11 transistors, add a .01 mfd. disc ceramic capacitor (500V) across the contacts of the push-pull on-off switch.

SUBJECT:

COURIER CLASSIC

To improve treble response of receiver audio, remove the jumper wire inside microphone switch which connects pin #2 to #4. See drawing below. Add jumper from #4 to frame to assure no hum pickup.

0 Jumper 4 6 0

Ray Dashner

Customer Service Mgr.

RD:rt