

Crystal Set; 'Swap Out' Conversion Chart for Walkie-Talkies

by B.W.

	Present Crystals per channel - set of two.		New Crystal Frequencies needed-reference to (A) and (B).	
	Tx-(A)	Rx-(B)	Tx using A as Rx Xtal	Rx using B as Tx Xtal
1	26.965	26.510	27.420	26.055
2	26.975	26.520	27.430	26.065
3	26.985	26.530	27.440	26.075
4	27.005	26.550	27.460	26.095
5	27.015	26.560	27.470	26.105
6	27.025	26.570	27.480	26.115
7	27.035	26.580	27.490	26.125
8	27.055	26.600	27.510	26.145
9	27.065	26.610	27.520	26.155
10	27.075	26.620	27.530	26.165
11	27.085	26.630	27.540	26.175
12	27.105	26.650	27.560	26.195
13	27.115	26.660	27.570	26.205
14	27.125	26.670	27.580	26.215
15	27.135	26.680	27.590	26.225
16	27.155	26.700	27.610	26.245
17	27.165	26.710	27.620	26.255
18	27.175	26.720	27.630	26.265
19	27.185	26.730	27.640	26.275
20	27.205	26.750	27.660	26.295
21	27.215	26.760	27.670	26.305
22	27.225	26.770	27.680	26.315
24	27.235	26.780	27.690	26.325
25	27.245	26.790	27.700	26.335
23	27.255	26.800	27.710	26.345
26	27.265	26.810	27.720	26.355
27	27.275	26.820	27.730	26.365
28	27.285	26.830	27.740	26.375
29	27.295	26.840	27.750	26.385
30	27.305	26.850	27.760	26.395
31	27.315	26.860	27.770	26.405
32	27.325	26.870	27.780	26.415
33	27.335	26.880	27.790	26.425
34	27.345	26.890	27.800	26.435
35	27.355	26.900	27.810	26.445
36	27.365	26.910	27.820	26.455
37	27.375	26.920	27.830	26.465
38	27.385	26.930	27.840	26.475
39	27.395	26.940	27.850	26.485
40	27.405	26.950	27.860	26.495