

TENNA POWER 10901/FIELDMASTER TR40

MIDLAND 102M/77-102.UNIC RV-CB40TB:

RV4-AMC

ROADALERT RA400/SPARKOMATIC

PLL = C5121

FINAL = 2SC2078

CHEAP UNIT. NO METER. HAS TX, RX, & MODULATION LIGHTS. HAS CHANNEL 9 SWITCH AND ELECTRONIC TUNING.

RV1-SQ RANGE

RV3-AMC

L2 & L3 ARE NON-ADJUSTABLE. WILL HAVE TO SPREAD OR COMPRESS TO TUNE. THERE ARE 3 OTHERS THAT ARE NOT LABELED.SPREAD OR COMPRESS ALL 5 COILS TO TUNE.(DON'T EXPECT MUCH.)

UNIDEN PC33X/PRO510E

VR1-SQ RANGE

VR2-TX METER

VR3-RX METER

VR4-LABELED RX SENS

TUNE L6,L9, & L1 FOR MAXIMUM FORWARD SWING WITH 30% INJECTED MODULATION.

GOOD LOW PRICE UNIT.

GALAXY SATURN BASE

QUICKIE Fo MOD:CUT PIN 11 OF IC5 AND BRIDGE CUT WITH A SPST SWITCH FOR LOW FREQUENCIES.

FORMAC 88 AM/FM EXPORT

PLL = PLL02

FINAL = 2SC1969

RV1-SQ RANGE

RV2-AMC

RV3-RX METER

RV4-TX METER

RV501-FM DEVIATION (ON FM BOARD)

CT1/MAIN BOARD-10.240 XTAL ADJUSTMENT

CT1/OSC BOARD-20.705 XTAL ADJUSTMENT (27.415-27.855)

TUNE L7,L11, & L12 FOR MAXIMUM FORWARD SWING WITH 30% INJECTED MODULATION.

USE STANDARD PLL02 MOD FOR LO FREQUENCY MOD.