

This Manual is provided by
CBTricks.com

Someone who wanted to help you repair your equipment put together this information.

Royce 1-653B Voltage Chart

If you would like to help us put more manuals online support us.

If you would like to help with this project let us know.

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

Thank you for any support you can give.

I-653B Voltage Chart

		Vb (V)		Vc (V)		Ve (V)		
		RX	TX	RX	TX	RX	TX	
Q101	2SC1856	1.6	0	7.0	0	0.9	0	
Q102	2SC710C	1.2	0	7.9	0	0.7	0	
Q201	2SC711E	0.6	0	4.6	0	0	0	
Q202	2SC711E	1.2	0	2.1	0	0.6	0	
Q203	2SC711D	0.7	0	4.5	0	0	0	
Q204	2SA695D	4.5	0	0	0	5.1	0	
Q205	2SC620D	0.7	0	0	0	0	0	NO SQUELCH
		0.1	0	2.1	0	0	0	SQUELCH
Q206	2SC945Q	0.1	0	2.1	0	0	0	NO SQUELCH
		0.7	0	0.1	0	0	0	SQUELCH
Q207	2SC945Q	2.5	0	8.6	0	1.9	0	
Q301	2SB561B		0~0.5 [*]		—		0	※MIC INPUT LEVEL 0~100mV/600Ω
Q302	2SC711E	1.2	1.2	11.9	11.9	0.5	0.5	NO SQUELCH
		1.1	1.2	13.3	11.9	1.4	0.5	SQUELCH
Q401	2SC1908	2.1	1.8	13.8	13.8	8.6	1.3	
Q402	2SC1728		—	12.7	12.7		—	
Q403	2SC756A ⁽²⁾		—	12.7	12.7		—	

		PIN NO										
		1	2	3	4	5	6	7	8	9	10	11
Q303	AN315	5.7	0	1.2	6.9	10.7	5.7	0	5.7	5.7	13.0	13.6
		V										